AT&T-21 and 48 STATE

ACCESS SERVICE REQUEST (ASR)

REJECT ERRORS

Version 29

ASR Error Codes and Message

Document Release Date: September 18, 2021

ASOG 63

VERSION HISTORY

Version Number	Effective Date	ASOG Version
1	1/10/07 Initial	33
2	3/10/07	34
3	9/15/07	35
4	3/15/2008	36
5	9/20/2008	37
6	3/21/2009	38
7	9/19/09	39
8	3/20/10	40
9	9/20/10	41
10	3/21/11	42
11	9/17/11	43
12	3/17/12	44
13	9/15/12	45
14	3/16/13	46
14	9/21/13	47
15	3/15/14	48
16	9/20/14	49
16A	11/21/14 *Revision provided to remove references to SNET (CT) as part of transfer to Frontier Communications	49
16B	3/21/15	50
17	9/19/15	51
18	03/21/16	52
19	09/19/16	53
20	03/18/17	54
21	09/18/17	55
22	03/17/18	56
23	09/15/18	57
24	03/16/19	58
25	09/21/19	59
26	03/21/20	60
27	09/21/20	61
28	03/20/21	62

SUMMARY of CHANGES

The following changes were made to the Error Codes and Message Section:

See **ASOG62 Release - Error Code Section** for full details

ICSC BY REGION

Region	State	Appropriate ICSC
Midwest	Illinois	LB01, LB02
	Indiana	NB01
	Michigan	MB01
	Ohio	OB01
	Wisconsin	WT33
Southwest	Arkansas	SW10
	Kansas	SW20
	Kansas City Mo	SW30
	St. Louis Mo	SW40
	Oklahoma	SW50
	Kansas	SW60
	Houston	SW70
	San Antonio	SW80
West	California South	SW02
	California North	SW04
	Nevada	SW06
Southeast	Georgia	SB01
	N & S Carolina	SB02
	N Florida	SB03
	S Florida	SB04
	Alabama	SC01
	Kentucky	SC02
	Louisiana	SC03
	Mississippi	SC04
	Tennessee	SC05
OOR	48 states	SW99

TABLE OF CONTENTS

SUMMARY of CHANGES_____ 2
ICSC BY REGION_____ 3
ERROR CODES AND MESSAGES_____ 16
ICM004_____ 16
NO MECH-SPEC RECORDS CONTAINED IN MESSAGE_____ 16
ICM005_____ 16
MESG. LENGTH INCORRECT.S/B LL + (1200*N)_____ 16
ICM006_____ 17
ACCESS DENIED FOR ARIS REAL-TIME INPUT INTERFACE_____ 17
ICS0003E_____ 17
ASR DOES NOT EXIST_____ 17
ICS0005E_____ 17
REQTYP MUST BE PRESENT_____ 17
ICS0006E_____ 17
ACTIVITY MUST BE PRESENT_____ 17
ICS0007E_____ 17
REQTYP MUST HAVE VALUE IN SECOND CHARACTER CONSISTENT WITH FOUR-STEP PROCESS RULES_____ 17
ICS0020E_____ 17
REFNUM REQUIRED_____ 17
ICS0021E_____ 17
REFNUM NOT VALID_____ 17
ICS0033E_____ 18
ADD FAILED – SCREEN ALREADY ADDED_____ 18
ICS0034E_____ 18
UPDATE FAILED – SCREEN NOT YET ADDED_____ 18
ICS0047E_____ 18
LEGACT MUST HAVE VALUE: N, C, D, M, K, R_____ 18
ICS0070E_____ 18
CANNOT CHANGE A COMPLETED ASR_____ 18
ICS0072E_____ 18
ASR MUST BE BLANK TO ADD NEW ASR_____ 18
ICS0084E_____ 19
CANNOT CHANGE SUPP TO BLANK_____ 19

ICS0085E_____ 19
SUPP MUST BE NUMERIC: 1,2,3,4 OR BLANK_____ 19
ICS0088E_____ 19
CANNOT CHANGE DD WITHOUT A SUPP OF 2 OR 3 OR 4_____ 19
ICS0091E_____ 19
CCNA REQUIRED_____ 19
ICS0092E_____ 19
CANNOT CHANGE A CANCELLED ASR_____ 19
ICS0105E_____ 19
RUNTIME ERROR OCCURRED IN FLEX EDIT VALIDATION MODULE_____ 19
ICS0136E_____ 20
VCAT INFORMATION REJECTED; AFO POS 5 MUST BE A Y TO PROCESS___ 20
ICS0137E_____ 20
ASR REJECTED, VCAT INFORMATION NOT PRESENT_____ 20
ICS0138E_____ 20
VCAT INFO FOR ICFA1-4 REJECTED; NO ASSOCIATED NAI INFORMATION FOUND_____ 20
ICS0197E_____ 20
SECURITY VIOLATION – CCNA INCORRECT_____ 20
ICS0264E_____ 20
TQ/EOD INFORMATION ONLY ALLOWED FOR REQUEST TYPE "M"_____ 20
ICS0318E_____ 21
CANNOT CHANGE A SUPP TO AN F UNLESS 2ND CHAR REQTYP = C, H, J__ 21
ICS0664E_____ 21
FIRST POSITION OF TQ MUST BE B, D, L, T, U OR W TO PROCESS_____ 21
ICS0709E_____ 21
FIRST POSITION OF THE TQ MUST BE S, T, OR U TO PROCESS_____ 21
ICS0750E_____ 21
REQTYP (FIRST POSITION) CANNOT BE CHANGED IN THIS STATUS_____ 21
ICS0905E_____ 21
FILE 'XXXXXXXX' IS UNDEFINED. PROCESS SKIP TO NEXT FILE_____ 21
ICS910E_____ 21
INPUT 'XXXXXXXX' IS EMPTY. PROCESS SKIP TO NEXT FILE_____ 21
ICS0915E_____ 22
INPUT FILE 'XXXXXXX'HAS BEEN PROCESSED BEFORE. FILE REJECTED (BATCH)_____ 22

ICS0916E_____ 22
ASR VERSION "NN" NOT VALID AT THIS TIME. FILE REJECTED_____ 22
ICS0920E_____ 22
RECORD PROCESSED_____22
ICS0925E_____ 22
RECORD TYPE UNDEFINED, PROCESS SKIP TO NEXT RECORD_____22
ICS0930E_____ 22
NOT ENOUGH RECORDS FOR THIS LAST INPUT RECORD TYPE_____ 22
ICS0940E_____ 22
THE RECORD MODE MUST BE "I" FOR INITIAL INPUT OR "C" FOR CHANGE _____22
ICS0941E_____ 23
INVALID REQTYP FOR PORT CONFIGURATION RECORD GROUP_____23
ICS0942E_____ 23
F45A, B, C RECORD GROUP ONLY ALLOWED FOR REFNUM 0001 FOR THIS REQTYP_____23
ICS0943E_____ 23
ASR REJECTED – PQPR/QPR SPECIFIED DOES NOT MATCH NUMBER OF PREFS_____23
ICS0944E_____ 23
ONLY ONE F45 OR F46 RECORD GROUP ALLOWED PER REFNUM_____ 23
ICS0945E_____ 23
F46A, B, C, RECORD GROUP ONLY ALLOWED FOR REFNUM 0001_____23
ICS0946E_____ 23
F45 AND F46 RECORDS ARE MUTUALLY EXCLUSIVE OF MSL (NSL>0)___ 23
ICS0947E_____ 24
F45 OR F46 (A OR B) RECORD WAS NOT PROVIDED_____ 24
ICS0948E_____ 24
ASR REJECTED – PI ON F45 (RECORDS) MUST BE "Y"_____24
ICS0949E_____ 24
RECORD REJECTED – PI ON F45 (RECORDS) MUST BE "Y"_____24
ICS0950E_____ 24
PASSWORD AND CCNA VALUE ARE NOT COMPATIBLE: FILE NOT PROCESSED_____24
ICS0951E_____ 24
RECORD REJECTED – NUMBER OF PREFS DOES NOT MATCH PQPR/QPR SPECIFIED_____24

ICS0955E_____ 24
ASR NUMBER MUST BE BLANK IN THE INITIAL REQUEST_____24
ICS0962E_____ 25
RECORD NOT FOUND. CCNA AND/OR PON FIELDS ARE IN ERROR_____ 25
ICS0963E_____ 26
MORE THAN ONE RECORD FOUND. CCNA AND PON FIELDS ARE NOT UNIQUE_____26
ICS0965E_____ 26
INVALID SEQUENCE. THIS FORM MUST FOLLOW AN INITIAL ASR FORM_ 26
ICS0966E_____ 27
RECORD NOT FOUND, ASR FIELD IN ERROR_____ 27
ICS0970E_____ 27
CCNA SPECIFIED IN THE CONTROL CARD AND IN THE FILE HEADER NOT MATCH_____ 27
ICS0973E_____ 27
MULTIPLE EOD RECORDS FOR REQUEST, RECORD REJECTED_____27
ICS0974E_____ 27
EOD RECORD MUST BE PROCESS BEFORE ANY EOI RECORDS, RECORDS REJECTED_____27
ICS0975E_____ 27
THE CCNA SPECIFIED IN CONTROL CARD IS 'XXXXXXXX'_____27
ICS0976E_____ 27
MULTIPLE TQ RECORDS FOR REQUEST, RECORD REJECTED_____ 27
ICS0977E_____ 28
MORE THAN 9 SAC RECORDS FOR REQUEST, RECORD REJECTED_____28
ICS0978E_____ 28
DUPLICATE SAC IN THE REQUEST, RECORD REJECTED_____28
ICS0980E_____ 28
PROCESS SKIP TO THE NEXT FILE_____ 28
ICS0985E_____ 28
THE FIRST RECORD IS NOT HEADER RECORD. THIS IS NOT A VALID INPUT FILE_____ 28
ICS0990E_____ 28
INVALID RECORD MODE IN HEADER, THIS IS NOT A VALID INPUT FILE (BATCH OR REAL-TIME INPUT)_____ 28
ICS0995E_____ 28

CCNA FIELD DOES NOT CONTAIN THE SAME VALUE AS THAT A OF THE HEADER 28
ICS0996E 29
SUPP FIELD VALUE MUST BE A 1, 2, 3, OR 4 WHEN RECORD MODE IS "C" 29
ICS0998E 29
SUPP FAILED 29
ICS0999E 29
RESEND FAILED 29
ICS1000E 29
#RECS FIELD IN HEADER RECORD IS INVALID, PROCESS STOP FOR THIS FILE (BATCH) 29
ICS1000E 29
#RECS FIELD IN HEADER RECORD IS INVALID, MESSAGE PROCESS STOPPED FOR THIS FILE (REAL-TIME INPUT) 29
ICS1005E 29
#REQS FIELD IN HEADER RECORD IS INVALID, PROCESS STOP FOR THIS FILE (BATCH) 29
ICS1005E 30
#REQS FIELD IN HEADER RECORD IS INVALID, MESSAGE PROCESS STOPPED FOR THIS FILE (REAL-TIME INPUT) 30
ICS1006E 30
ASR VER FIELD IN HEADER RECORD IS INVALID, REQUEST PROCESSING STOPPED (REAL-TIME INPUT) 30
ICS1012E 30
ADD FAILED 30
ICS1013E 30
SUPP FAILED 30
ICS1014E 30
RESEND FAILED 30
ICS1015E 30
REFNUM DOES NOT EXIST – REGIONAL RECORD REJECTED 30
ICS1016E 30
NO OEC_ICSC FOUND – NO F40 RECORD SENT CONTAINING MATCHING ICSC 30
ICS1017E 31
F40 RECORDS FOUND – NON MULITEC REQUEST, HOWEVER F40 RECORDS FOUND 31
ICS1018E 31

INVALID ASC- ASC EC VALUE ON ASR RECORD DOES NOT MATCH THAT ON F40A 31
ICS1019E 31
DUPLICATE ICSC – F40 RECORD HAS DUPLICATE ICSC VALUES 31
ICS1020E 31
NATIONAL ASR RECORD NOT PRESENT 31
ICS1021E 31
RECORD NOT PROCESSED, THE ASSOCIATED ASR RECORD WAS REJECTED 31
ICS1022E 31
RECORD NOT PROCESSED. THE REFNUM WAS OUT OF SEQUENCE 31
ICS1023E 32
RECORD NOT PROCESSED. The VCNUM OR UREF WAS OUT OF SEQUENCE 32
ICS1025E 32
ASR REJECTED – FLEX FATAL ERROR DETECTED 32
ICS1026E 32
INCORRECT NUMBER OF UNIT TERMINATION POINTS PROVIDED 32
ICS1028E 32
INVALID SERVICE TYPE FOR ETHERNET VIRTUAL CONNECTION SERVICE 32
ICS1029E 32
INVALID EVCI FOR ETHERNET VIRTUAL CONNECTION SERVICE 32
ICS1030E 33
INVALID RECORD COMBINATION FOR ETHERNET VIRTUAL CONNECTION SERVICE 33
ICS1031E 33
SUBMISSION OF EVC DATA REQUIRES THE EVCI FIELD BE POPULATED 33
ICS1032E 33
INVALID CHANGE TO EVCI 33
ICS1033E 33
EVCNUM VALUE IS INVALID 33
ICS1034E 33
ASR REJECTED – NO F47A RECORD FOUND FOR EVC SERVICE 33
ICS1035E 33
SUPP FAILED – NO F47A RECORD FOUND FOR EXISTING UREF(S) ON EVC REQUEST 33
ICS1040E 34

NATIONAL CIRCUIT LEVEL RECORD REFNUM XXXX WITHOUT CORRESPONDING RECORD 34
ICS1681E 34
RTR MUST HAVE VALUE: F, N OR S 34
ICS1279E 34
WHEN CHANGING ASR TO MULTI EC IN ACTIVE SUPP STATUS, ASC EC MUST = ICSC 34
ICS1681E 34
RTR MUST HAVE VALUE: F, N OR S 34
ICS1719E 34
QNAI NOT VALID WITHOUT ACI OR ARI DATA WHEN QTY GREATER THAN 1 34
ICS1726E 34
FOR NAI, POS 3 OF AFO MUST BE "Y" AND QNAI POPULATED 34
ICS1747E 35
SCREEN NOT VALID FOR REQTYP OR QSA MUST BE GREATER THAN 0 35
ICS1831E 35
EVCI VALID VALUES ARE: A, B OR BLANK (REQTYP S), B OR BLANK (REQTYP E) 35
ICS1888E 35
ASR REJECTED: INVALID CHANGE TO EVCI 35
ICS1890E 35
EVCI = "A" IS ONLY VLAID FOR REQTYP "S" 35
ICS5786E 35
FIELD CANNOT BE CHANGED ON A SUPP 2 35
ICS7001E 36
PRODUCT CAN NOT BE REQUESTED VIA THIS ORDERING TOOL 36
ICS7002E 36
RTR IS A REQUIRED FIELD – VALID ENTRIES ARE N, F, S OR NUMERIC 36
ICS7006E 36
ICSC CODE INVALID FOR THIS EXACT DATA BASE 36
ICS7007E 36
ASR SENT TO WRONG DATA BASE LOCATION 36
ICS7008E 36
LTP CAN ONLY EQUAL BLANK, N OR F ON REQUEST TYPE OF L 36
ICS7010E 37
GETO W IS THE ONLY ALLOWABLE AT&T OPTION 37

ICS7011E_____ 37
IWBAN ENTRY OF BLANK OR "E" ARE PROHIBITED WHEN GETO IS POPULATED_____ 37
ICS7012E_____ 37
TGTYP VALUE OF "H" IS NOT VALID IN AT&T (*REGION)* IF TRFTYP-ORIG NOT=E9_____37
ICS7013E_____ 37
A TGTYP VALUE OF "H" IS NOT SUPPORTED BY AT&T (*Region)*_____ 37
ICS7014E_____ 37
A VALID DRC CODE IS REQUIRED WHEN THE RTR = S OR 1-10_____ 37
ICS7015E_____ 37
NC/NCI/SECNCI NOT FOUND IN DATABASE_____ 37
ICS7016E_____ 37
NC/NCI/SECNCI COMBINATION IS NOT VALID FOR NEW ACTIVITY_____37
ICS7018E_____ 38
THE RTR OF S AND 1-10 ARE NOT VALID FOR D ACTIVITY, USE F OR N__ 38
ICS7020E_____ 38
AT&T DOES NOT OFFER AT THIS TIME_____38
ICS7020EA_____ 38
AT&T DOES NOT OFFER AT THIS TIME_____38
ICS7020EA_____ 38
AT&T DOES NOT OFFER AT THIS TIME_____38
ICS7021E_____ 39
DESIRED DATE DUE MUST BE VALID DAY, MONTH AND YEAR_____ 39
ICS7022E_____ 39
DDD CAN NOT EXCEED 180 DAYS-PLEASE CORRECT_____ 39
ICS7023E_____ 39
BAN REQUIRED_____39
ICS7024E_____ 39
SECNCI NOT VALID FOR THIS NC CODE_____ 39
ICS7050E_____ 40
INCORRECTLY FORMATTED CFA_____40
ICS7051E_____ 40
CFA FACILITY DESIGNATION (FACDESG) IS NOT VALID_____40
ICS7052E_____ 40
CFA FACILITY TYPE (FACTYP) IS NOT VALID_____ 40

ICS7053E_____ 40
CFA CHANNEL (CHAN) IS NOT VAILD_____40
ICS7054E_____ 40
CFA LOCATION A CLLI (LOC A) IS NOT VALID_____ 40
ICS7055E_____ 40
CFA LOCATION Z CLLI (LOC Z) IS NOT VALID_____40
ICS7056E_____ 41
SYSTEM ERROR WHILE PROCESS CFA, PLEASE CONTACT SUPPORT_____41
ICS7057E_____ 41
CFA NOT FOUND_____41
ICS7058E_____ 41
CFA CHAN UNAVAIL_____41
ICS7059E_____ 41
SERVICE ADDRESS NOT FOUND_____41
ICS7060E_____ 41
AN EXACT ADDRESS MATCH NOT FOUND_____41
ICS7075E_____ 41
*ASR CANNOT CONTAIN BOTH CFA & CCEA*_____ 41
ICS7076E_____ 42
*SPOT FIELD REQUIRED WHEN SECLOC IS CUSTOMER PREM (E)*_____42
ICS7077E_____ 42
*FNI MUST BE POPULATED FOR THIS SERVICE*_____ 42
ICS7078E_____ 43
*CFA ACTL CLLI MUST MATCH ACTL CLLI ON ASR*_____43
ICS7079E_____ 43
*CFA REQUIRED FOR THIS NCI, WHEN NC = HC++*_____43
ICS7080E_____ 44
*DS1 CIRCUIT CANNOT RIDE DS1 CFA*_____ 44
ICS7081E_____ 44
*WHEN SPEC FIELD INDICATES DISASTER REMAP, PRILOC MUST BE A CUST PREM (E)*_____ 44
ICS7082E_____ 44
*CENTREX NC CODES REQUIRE DATA IN THE CTX-TEL FIELD*_____44
ICS7083E_____ 45
*CLLI IS REQUIRED IN PRILOC WHEN ORDERING DSRS REGENERATOR*__45

ICS7085E_____ 45
*DS0 CIRCUIT CANNOT RIDE DS3 CFA*_____ 45
ICS7086E_____ 46
*C.NPANXX FIELD MUST BE POPULATED*_____ 46
ICS7087E_____ 46
*IWBAN IS IN INVALID FORMAT, PLEASE CORRECT*_____46
ICS7088E_____ 46
*VTA REQUIRED WHEN PROJECT = "NOMONEYDOWN"*_____ 46
ICS7089E_____ 47
*REQTYP M INVALID WHEN SPEC EQUALS "RCADS1"*_____ 47
ICS7090E_____ 47
*JACK CODE MUST BE EITHER 3 OR 5 CHARACTERS*_____ 47
ICS7091E_____ 47
*WST REQUIRED FOR WIRELESS SERVICE-MUST BE F, G, H, L*_____47
ICS7092E_____ 48
*ASR CANNOT CONTAIN BOTH SCFA & SCCEA*_____ 48
ICS7093E_____ 48
*INVALID LTP WHEN NC1 IS POPULATED*_____ 48
ICS7094E_____ 48
*INVALID NC CODE FOR GIGAMAN SERVICE*_____ 48
ICS7095E_____ 49
*INVALID SONNET CFA FACILITY TYPE-CORRECT FROM STS+ OR VT1+ TO OC+*_____ 49
ICS7096E_____ 49
*INVALID SONNET SCFA FACILITY TYPE-CORRECT FROM STS+ OR VT1+ TO OC+*_____ 49
ICS7098E_____ 50
*VTA FOR FAST SERVICE MUST BE 36*_____ 50
ICS7101E_____ 50
*FNI MUST BEGIN WITH N WHEN ORDERING THIS SERVICE*_____ 50
ICS7102E_____ 51
*FNI MUST BEGIN WITH W WHEN ORDERING THIS SERVICE*_____51
ICS7103E_____ 51
*INVALID FNI FORMAT – PLEASE CORRECT*_____ 51
ICS7105E_____ 51

LTP REQUIRED FOR SWITCHED FACILITY WHEN SECLOC CLLI IS 11 CHARACTERS 51

ICS7106E 52

SPEC "NSDWRG" – CANNOT EXPEDITE WHEN DIVERSITY INVOLVED 52

ICS7107E 52

SPEC 'NSDWRG' REQUIRES GETO OF "W" AT ENDUSER LOCATION 52

ICS7108E 53

SPEC 'NSDWRG' REQUIRES GETO OF "W" AT ENDUSER LOCATION 53

ICS7109E 53

APS SERVICE IS GRANDFATHERED – ACT OF "N" OR "T" NOT ALLOWED 53

ICS7110E 53

SECLOC MUST EQUAL "E" WHEN QSA IS POPULATED 53

ICS7111E 54

SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE 54

ICS7112E 54

SPEC DATA REQUIRED WHEN SEI IS POPULATED 54

ICS7114E 54

ECCKT WITH SERVICE CODE OF VL NOT VALID ON ASR FORM. USE EVC FORM. 54

ICS7116E 54

FATAL EDIT: RTR FIELD MUST BE N OR F FOR DISCONNECT ORDERS 54

ICS7117E 55

FATAL EDIT: DUE DATE ON ORDER CAN NOT BE EARLIER THAN TODAY 55

ICS7118E 55

FATAL EDIT: USE WSR FOR WIRELESS SERVICE REQUESTS 55

ICS7119E 55

FATAL EDIT: ALTERNATE ACTL OPTION NOT CURRENTLY AVAILABLE ON RINGS 55

ICS7122E 55

FATAL EDIT: TELIS APP NO LONGER AVAIL. FOR INITIAL REQUESTS 55

ICS7123E 56

FATAL EDIT: MUXLOC MUST BE BLANK BASED ON SERVICE ORDERED 56

ICS7124E 56

FATAL EDIT: MUXLOC INCORRECTLY POPULATED BASED ON SERVICE ORDERED 56

ICS7125E 56

FATAL EDIT: MUXLOC INVALID DUE TO INCORRECTLY POPULATED CFA 56

ICS7126E_____ 56
FATAL EDIT: CFA IS NON-STANDARD FORMAT_____ 56
ICS7127E_____ 56
FATAL EDIT: SCFA IS NON-STANDARD FORMAT_____56
ICS7128E_____ 57
FATAL EDIT: ICFA1 - 4 IS NON-STANDARD FORMAT_____57
ICS7129E_____ 57
FATAL EDIT: ETHERNET VIRTUAL CONNECTION IS NOT SUPPORTED AT THIS TIME_____ 57
ICS7131E_____ 57
FATAL EDIT:MAXIMUM SUPPS RECEIVED - CANCEL AND REISSUE PON_____ 57
ICS7132E_____ 57
FATAL EDIT: VIRTUAL CONCANTENATION IS NOT SUPPORTED AT THIS TIME _____57
ICS7136E_____ 58
FATAL EDIT: SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE____58
ICS7137E_____ 58
FATAL EDIT: SPEC DATA REQUIRED WHEN SEI IS POPULATED_____ 58
ICS7139E_____ 58
FATAL EDIT: COMBO ASR NOT SUPPORTED FOR ETTCS_____ 58
ICS7140E_____ 58
FATAL EDIT: COMBO ASR NOT SUPPORTED FOR RTP_____ 58
ICS7140E_____ 58
FATAL EDIT: COMBO ASR NOT SUPPORTED FOR RTP_____58
ICS7141E_____ 59
FATAL EDIT: REQUIRED ASOG FIELDS MISSING (CITY, STATE, ZIP)_____ 59
ICS7142E_____ 59
FATAL EDIT: ASC-EC REQUIRED WHEN ICOL POPULATED_____ 59
ICS7143E_____ 59
FATAL EDIT: SAPR, SASF, SASD, SATH, SASS PROHIBITED WHEN AFT = D AND SANO IS BLANK_____ 59
ICS7144E_____ 59
FATAL EDIT: SAG ONLY ADDRESS – VERIFY IF NEW CONSTRUCTION _____ 59
ICS7145E_____ 59
FATAL EDIT: ASC-EC REQUIRED WHEN OTC POPULATED_____ 59
ICS7146E_____ 60
FATAL EDIT: ATT DOES NOT SUPPORT AFT = “E”_____ 60

ICS7147E ____ 60

FATAL EDIT: ADDRESS NOT VALID FOR LATA, PLEASE VERIFY ICSC & REGION ____ 60

ICS7148E ____ 60

FATAL EDIT: PRODUCT NOT ELIGIBLE AT ROUTE, REQUEST INVALID ____ 60

ICS7149E ____ 60

FATAL EDIT: DUE TO SYSTEM LIMITATIONS AT&T DOES NOT SUPT AAI GREATER THAN 60 CHARS ____ 60

ICS8447E ____ 61

PROFILE REQUIRED WHEN ORDERING PPCOS ____ 61

ICS7219E ____ 69

GETO MUST HAVE VALUE: A, E, F, M, N, O, P, R, S, T, U, V, W, Y, OR Z ____ 69

ICS0220E ____ 70

VTAI VALID VALUES ARE A, B, C ____ 70

ASOG49 Error Code Section ____ 61
ASOG50 Error Code Section ____ 63
ASOG51 Error Code Section ____ 65
ASOG52 Error Code Section ____ 66
ASOG53 Error Code Section ____ 69
ASOG54 Error Code Section ____ 69
ASOG55 Error Code Section ____ 69
ASOG56 Error Code Section ____ 69
ASOG57 Error Code Section ____ 69
ASOG58 Error Code Section ____ 69
ASOG59 Error Code Section ____ 69
ASOG60 Error Code Section ____ 69
ASOG61 Error Code Section ____ 70
ASOG62 Error Code Section ____ 70

==========

ERROR CODES AND MESSAGES

ICM004	**NO MECH-SPEC RECORDS CONTAINED IN MESSAGE**
Region	All
Form	NA
Field	NA
Description	This input message does not contain MECH SPEC records.
Last Update	

ICM005	**MESG. LENGTH INCORRECT.S/B LL + (1200*N)**
Region	All
Form	NA
Field	NA
Description	The input message length is incorrect. Expected length is equal to LL

	plus a multiple of 1200 bytes.
Last Update	

ICM006	**ACCESS DENIED FOR ARIS REAL-TIME INPUT INTERFACE**
Region	All
Form	NA
Field	NA
Description	Access has been denied to the ARIS-Real-Time Input Interface.
Last Update	

ICS0003E	**ASR DOES NOT EXIST**
Region	ALL
Form	NA
Field	NA
Description	The Access Service Request (ASR) number entered on the update could not be found in the ASR data base.
Last Update	

ICS0005E	**REQTYP MUST BE PRESENT**
Region	All
Form	ASR
Field	REQTYP
Description	The REQTYP value is missing.
Last Update	

ICS0006E	**ACTIVITY MUST BE PRESENT**
Region	All
Form	ASR
Field	ACT
Description	The activity (ACT) value is missing.
Last Update	

ICS0007E	**REQTYP MUST HAVE VALUE IN SECOND CHARACTER CONSISTENT WITH FOUR-STEP PROCESS RULES**
Region	ALL
Form	ASR
Field	REQTYP
Description	Valid values in the second character position of the Request Type (REQTYP) field are: A, F, G, D, J or K.
Last Update	

ICS0020E	**REFNUM REQUIRED**
Region	ALL
Form	ACI, ARI, CNF, CNR, MSL, NAI, PORTS, SALI
Field	REFNUM.
Description	The user tried to process transaction without populating the REFNUM field. This field must contain a numeric value.
Last Update	

ICS0021E	**REFNUM NOT VALID**
Region	ALL
Form	ACI, ARI, CNF, CNR, MSL, NAI, PORTS, SALI

Field	REFNUM
Description	An invalid value was entered in the REFNUM field. A valid value for this field is any numeric greater than 0001.
Last Update	

ICS0033E	**ADD FAILED – SCREEN ALREADY ADDED**
Region	ALL
Form	ALL
Field	NA
Description	In the batch environment, the message should be interpreted as "THE RECORD ALREADY ADDED" The user attempted to add a batch record which is already there. This message can occur for all the batch records except for the "S" type.
Last Update	

ICS0034E	**UPDATE FAILED – SCREEN NOT YET ADDED**
Region	ALL
Form	ALL
Field	NA
Description	In the batch environment, the message should be interpreted as 'THE RECORD NOT YET ADDED'. The user is attempting to update a batch record which is not yet present in the system. This message can occur for all the batch records except for 'S' type.
Last Update	

ICS0047E	**LEGACT MUST HAVE VALUE: N, C, D, M, K, R**
Region	ALL
Form	MSL
Field	LEGACT
Description	The LEGACT value is incorrect. Must have a value of N, C, D, M, K or R.
Last Update	
ICS0050E	**Prohibited Field Present**
Region	ALL
Form	NA
Field	NA
Description	The S-VLAN field is populated on the EVC. This was a 9 State edit expanded to 22 state
Last Update	3/16/2013

ICS0070E	**CANNOT CHANGE A COMPLETED ASR**
Region	ALL
Form	NA
Field	NA
Description	No update is allowed on records with complete status.
Last Update	

ICS0072E	**ASR MUST BE BLANK TO ADD NEW ASR**
Region	ALL
Form	NA
Field	ASR NO.
Description	The ASR field has been filled in while attempting an add transaction.

	This is not allowed.
Last Update	

ICS0084E	**CANNOT CHANGE SUPP TO BLANK**
Region	ALL
Form	ASR
Field	SUPP
Description	The user has attempted to update an existing supplemental (SUPP) field to a blank. This is not allowed.
Last Update	

ICS0085E	**SUPP MUST BE NUMERIC: 1,2,3,4 OR BLANK**
Region	ALL
Form	ASR
Field	SUPP
Description	The SUPP field is a local validation. If entered it must have a value of 1,2,3,4 or blank.
Last Update	

ICS0088E	**CANNOT CHANGE DD WITHOUT A SUPP OF 2 OR 3 OR 4**
Region	ALL
Form	ASR
Field	SUPP
Description	The user attempted to update the DD (due date) field, but the supplement type was not 2, 3, or 4.
Last Update	

ICS0091E	**CCNA REQUIRED**
Region	ALL
Form	ASR
Field	CCNA
Description	CCNA is required for this transaction and is not entered.
Last Update	

ICS0092E	**CANNOT CHANGE A CANCELLED ASR**
Region	ALL
Form	ASR
Field	SUPP
Description	The user attempted an update on a 'cancelled' data base record.
Last Update	

ICS0105E	**RUNTIME ERROR OCCURRED IN FLEX EDIT VALIDATION MODULE**
Region	ALL
Form	ANY
Field	NA
Description	A run time error was encountered while executing a FLEX EDIT module.
Last Update	

ICS0136E	**VCAT INFORMATION REJECTED; AFO POS 5 MUST BE A Y TO PROCESS**
REGION	ALL
FORM	VCAT
FIELD	NA
DESCRIPTION	The fifth position of the AFO field is blank and the service request contains VCAT information. The ASR information is accepted but the VCAT information is fatally rejected. Resend the request with the fifth position of the AFO field set to 'y' or resend the request without the VCAT information (xml) or records (f48a-c , batch).
Last Update	9/20/08

ICS0137E	**ASR REJECTED, VCAT INFORMATION NOT PRESENT**
Region	ALL
Form	VCAT
Field	NA
Description	The fifth position of the AFO field, contains a 'Y' and the service request contains no VCAT information or records. The ASR is fatally rejected. Resend the request with the fifth position of the AFO field set to blank or resend the request with VCAT information (xml) or records F48A-C, Batch).
Last Update	9/20/08

ICS0138E	**VCAT INFO FOR ICFA1-4 REJECTED; NO ASSOCIATED NAI INFORMATION FOUND**
Region	ALL
Form	VCAT
Field	NA
Description	VCAT information exists in the transaction or load file, but there is no associated NAI information present. Add the associated NAI information (xml) or record (F48B-C, batch) to the request or remove the VCAT information.
Last Update	9/20/08

ICS0197E	**SECURITY VIOLATION – CCNA INCORRECT**
Region	ALL
Form	NA
Field	NA
Description	The CCNA value in the record does not pass the security check.
Last Update	

ICS0264E	**TQ/EOD INFORMATION ONLY ALLOWED FOR REQUEST TYPE "M"**
Region	ALL
Form	ASR
Field	REQTYP
Description	TQ AND End Office information is only allowed for request type "M".

Last Update	

ICS0318E	**CANNOT CHANGE A SUPP TO AN F UNLESS 2ND CHAR REQTYP = C, H, J**
Region	ALL
Form	ASR
Field	REQTYP
Description	When the service request (4 step) process is utilized in order to keep track of the ASR request moving through the 4 steps internally the SUP field is marked with an "F" by our system. When firm order ASR, step 3 of the process is issued the second position of the REQTYP should be either "C", "H", "J". If it is not the above error is generated. Review the second position of the REQTYP and correct accordingly.
Last Update	

ICS0664E	**FIRST POSITION OF TQ MUST BE B, D, L, T, U OR W TO PROCESS**
Region	ALL
Form	ASR
Field	TQ
Description	The screen is prohibited if the first position of TQ is not B, D, L, T, U or W.
Last Update	

ICS0709E	**FIRST POSITION OF THE TQ MUST BE S, T, OR U TO PROCESS**
Region	ALL
Form	ASR
Field	TQ
Description	The screen is prohibited if the first position of TQ on the ASR form is not S, T or U.
Last Update	

ICS0750E	**REQTYP (FIRST POSITION) CANNOT BE CHANGED IN THIS STATUS**
Region	ALL
Form	ASR
Field	REQTYP
Description	The first position of REQTYP can only be changed while ASR is in entered status.
Last Update	

ICS0905E	**FILE 'XXXXXXXX' IS UNDEFINED. PROCESS SKIP TO NEXT FILE**
Region	ALL
Form	NA
Field	NA
Description	The DD card for the named file 'XXXXXXXX' is missing.
Last Update	

ICS910E	**INPUT 'XXXXXXXX' IS EMPTY. PROCESS SKIP TO NEXT FILE**
Region	ALL
Form	NA

Field	NA
Description	The input file named 'XXXXXXXX' contained not data.
Last Update	

ICS0915E	**INPUT FILE 'XXXXXXX'HAS BEEN PROCESSED BEFORE. FILE REJECTED (BATCH)**
Region	ALL
Form	NA
Field	NA
Description	The batch input file/message submitted has been processed before. The error will only appear for the header. XXXXXXXX will be replaced by the name of the file when the message is generated. No other message will be created since the rest of the file/message was ignored by the system.
Last Update	

ICS0916E	**ASR VERSION "NN" NOT VALID AT THIS TIME. FILE REJECTED**
Region	ALL
Form	NA
Field	NA
Description	The current file header identified itself as belonging to ASR Version "NN", which is not a currently valid ASR version. This file is rejected.
Last Update	

ICS0920E	**RECORD PROCESSED**
Region	ALL
Form	NA
Field	NA
Description	This is not an error message. This is an acknowledgement message that the input file header processed. This message should always be present if the input file header record is correct.
Last Update	

ICS0925E	**RECORD TYPE UNDEFINED, PROCESS SKIP TO NEXT RECORD**
Region	ALL
Form	NA
Field	NA
Description	The record type (REC_TYPE field) in the batch record does not contain a valid value.
Last Update	

ICS0930E	**NOT ENOUGH RECORDS FOR THIS LAST INPUT RECORD TYPE**
Region	ALL
Form	NA
Field	NA
Description	The required records were not found in the input file for this request.
Last Update	

ICS0940E	**THE RECORD MODE MUST BE "I" FOR INITIAL INPUT OR "C" FOR CHANGE**
Region	ALL
Form	NA

Field	NA
Description	The record mode (REC_MODE field) must have the value of "I" for initial add operation or "C" for update operation
Last Update	

ICS0941E	**INVALID REQTYP FOR PORT CONFIGURATION RECORD GROUP**
Region	ALL
Form	ASR
Field	REQTYP
Description	Primary port configuration data valid for REQTYPs E, M, S, R; Secondary port configuration data valid for REQTYPs E or S.
Last Update	

ICS0942E	**F45A, B, C RECORD GROUP ONLY ALLOWED FOR REFNUM 0001 FOR THIS REQTYP**
Region	ALL
Form	ASR
Field	REQTYP
Description	Port configuration data valid for REQTYPs E, M and S may contain data only on the backbone REFNUM
Last Update	

ICS0943E	**ASR REJECTED – PQPR/QPR SPECIFIED DOES NOT MATCH NUMBER OF PREFS**
Region	ALL
Form	ARI, EUSA, RING, TRANSPORT, TRUNK
Field	PQPR OR QPR
Description	The ASR was rejected because an inconsistency has been detected between the quantity value expressed in QPR or PQPR and the actual number of PREFs provided.
Last Update	

ICS0944E	**ONLY ONE F45 OR F46 RECORD GROUP ALLOWED PER REFNUM**
Region	ALL
Form	NA
Field	NA
Description	A duplicate group of port data was detected
Last Update	

ICS0945E	**F46A, B, C, RECORD GROUP ONLY ALLOWED FOR REFNUM 0001**
Region	ALL
Form	NA
Field	NA
Description	Secondary port data is only allowed on the backbone REFNUM
Last Update	

ICS0946E	**F45 AND F46 RECORDS ARE MUTUALLY EXCLUSIVE OF MSL (NSL>0)**
Region	ALL
Form	NA
Field	NA

Description	Port configuration and multiple service legs are mutually exclusive for the live of the ASR.
Last Update	

ICS0947E	**F45 OR F46 (A OR B) RECORD WAS NOT PROVIDED**
Region	ALL
Form	NA
Field	NA
Description	A port configuration record was encountered without the proper preceding record(s)
Last Update	

ICS0948E	**ASR REJECTED – PI ON F45 (RECORDS) MUST BE "Y"**
Region	ALL
Form	PORTS, SALI
Field	PI
Description	The ASR was rejected because a condition was encountered on a primary port configuration record missing a "Y" in the PI field.
Last Update	

ICS0949E	**RECORD REJECTED – PI ON F45 (RECORDS) MUST BE "Y"**
Region	ALL
Form	PORTS, SALI
Field	PI
Description	Primary port configuration record must contain a "Y" in the PI field.
Last Update	

ICS0950E	**PASSWORD AND CCNA VALUE ARE NOT COMPATIBLE: FILE NOT PROCESSED**
Region	ALL
Form	NA
Field	NA
Description	Security violation. The password in the header record is incorrect.
Last Update	

ICS0951E	**RECORD REJECTED – NUMBER OF PREFS DOES NOT MATCH PQPR/QPR SPECIFIED**
Region	ALL
Form	PORTS, SALI
Field	PQPR, QPR
Description	An inconsistency has been detected between the quantity value expressed in QPR or PQPR and the actual number of PREFs provided.
Last Update	

ICS0955E	**ASR NUMBER MUST BE BLANK IN THE INITIAL REQUEST**
Region	ALL
Form	ASR
Field	ASR NUMBER
Description	When adding an "S" type record or a "D" type record, the ASR field must contain blanks.
Last Update	

ICS0962E	**RECORD NOT FOUND. CCNA AND/OR PON FIELDS ARE IN ERROR**
Region	ALL
Form	NA
Field	NA
Description	The message indicates one of the following errors occurred.

If Purchase Order Number (PON) for the IC is always unique.

- If REC_MODE = "I"
  Reason:
  If a previous Add request has been issued for an 'S' type record, then the value of the PON field in the previous 'S' type record and in the current rejected record are different. The process assumes the request is to add a record to an existing Access Service Request (ASR) and trying to locate that record by using CCNA and PON fields. The record can not be found.
  Solution:
  Check if the PON of this rejected record should be different from that of the previous 'S' type records. Correct the value in the PON field.

  Reason:
  If no previous Add request has been issued for an 'S' type record and the record identified by the CCNA and PON fields can not be found, the record is rejected.
  Solution:
  If a previous Add request for 'S' type record is missing, Add that request. If this request is to add a record to an existing record, then the PON field is invalid.

- If REC_MODE = 'C'
  Reason:
  The user attempted to Update a record which is not there. The PON field is in error.
  Solution:
  Correct the PON field.

If Purchase Order Number (PON) for the IC is not always unique

- If REC_MODE = 'I'
  Reason:
  If a previous Add request has been issued for an 'S' type record, then the value of the PON field in the previous 'S' type record and in the current rejected record is different. The process assumes that the request is to Add records to an existing Access Service Request (ASR), and trying to locate that record by using CCNA and PON fields. The record can not be found.
  Solution:
  Check if the PON of this rejected record should be different from that of the previous 'S' type records. Correct the value in the PON field. If the request is to Add a record to an existing Access Service Request, correct the PON field and provide the ASR number, if possible.

Reason:
If no previous Add request has been issued for an 'S' type record and the record identified by the CCNA and PON fields can not be found, the record is rejected.
Solution:
If a previous Add request for 'S' type records is missing, add that request. If this request is to Add records to an existing record, then correct the PON field and provide the ASR number, if possible.

- If REC_MODE = 'C'
  Reason:
  The user attempted to Update a record which is not there. The PON field is in error.
  Solution:
  Correct the PON field or provide the ASR number

Last Update

ICS0963E	**MORE THAN ONE RECORD FOUND. CCNA AND PON FIELDS ARE NOT UNIQUE**
Region	ALL
Form	NA
Field	NA
Description	This message indicates one of the following errors occurred:

If the Purchase Order Number (PON) for the IC is always unique.
Reason:
The process assumes a request is issued for an existing Access Service Request (ASR), and then tried to locate that record using CCNA and PON fields. More than one record has been found.
Solution:
Two Access Service Requests with the same PON value are in the data base. Either the IC's system has produced duplicate PONs for different records, or the ICSC has manually created a duplicate record.

If the Purchase Order Number for the IC is not always unique
Reason:
The process tried to locate an existing Access Service Request by using the CCNA and PON fields. More than one has been found. The process can not determine which one is to be used.
Solution:
Provide the correct ASR number.

Last Update

ICS0965E	**INVALID SEQUENCE. THIS FORM MUST FOLLOW AN INITIAL ASR FORM**
Region	ALL
Form	NA
Field	NA

Description	Before adding a record with the record type of 'L', 'O', 'A', 'P', 'X', 'R', or 'T', an 'S' type record must be added to the system. This error can also occur if the previous 'S' type record was rejected.
Last Update	

ICS0966E	**RECORD NOT FOUND, ASR FIELD IN ERROR**
Region	ALL
Form	ASR
Field	ASR/PON
Description	This message will occur on an update when both the PON and the ASR number fields are populated on the ASR. This message identifies that the ASR number cannot be found in the data base. When both fields (PON and ASR NO) are populated the system uses the ASR NO as a record key.
Last Update	

ICS0970E	**CCNA SPECIFIED IN THE CONTROL CARD AND IN THE FILE HEADER NOT MATCH**
Region	ALL
Form	NA
Field	NA
Description	The CCNA named 'XXXXXXXX' on the control card is incorrect or the CCNA in the header record did not pass security validation (messages ICS0975E and ICS0980e will also be output.
Last Update	

ICS0973E	**MULTIPLE EOD RECORDS FOR REQUEST, RECORD REJECTED**
Region	ALL
Form	EOD
Field	NA
Description	More than one end office detail record (F41C) was received for this request.
Last Update	

ICS0974E	**EOD RECORD MUST BE PROCESS BEFORE ANY EOI RECORDS, RECORDS REJECTED**
Region	ALL
Form	NA
Field	NA
Description	An end office information record (F42A thru Z) preceded the end office detail record (F41C)
Last Update	

ICS0975E	**THE CCNA SPECIFIED IN CONTROL CARD IS 'XXXXXXXX'**
Region	ALL
Form	NA
Field	NA
Description	This message appears in support of message ICS0970E
Last Update	

ICS0976E	**MULTIPLE TQ RECORDS FOR REQUEST, RECORD REJECTED**
Region	ALL

Form	TQ
Field	NA
Description	More than one translation questionnaire (F41A) was received for this request
Last Update	

ICS0977E	**MORE THAN 9 SAC RECORDS FOR REQUEST, RECORD REJECTED**
Region	ALL
Form	TQ – SAC NXX CODE ACTIVITY SECTION
Field	NA
Description	Nine SAC records is the maximum allowable per ASR. Any additional SAC records are rejected. Correct the input file to contain no more than 9 SACS
Last Update	9/19/09

ICS0978E	**DUPLICATE SAC IN THE REQUEST, RECORD REJECTED**
Region	ALL
Form	TQ – SAC NXX CODE ACTIVITY SECTION
Field	NA
Description	A duplicate SAC Code was encountered for the ASR. Remove the duplicate SAC record
Last Update	9/19/09

ICS0980E	**PROCESS SKIP TO THE NEXT FILE**
Region	ALL
Form	NA
Field	NA
Description	This message appears in support of message ICS0970E
Last Update	

ICS0985E	**THE FIRST RECORD IS NOT HEADER RECORD. THIS IS NOT A VALID INPUT FILE**
Region	ALL
Form	NA
Field	NA
Description	The header record type is not an "*"
Last Update	

ICS0990E	**INVALID RECORD MODE IN HEADER, THIS IS NOT A VALID INPUT FILE (BATCH OR REAL-TIME INPUT)**
Region	ALL
Form	NA
Field	NA
Description	The header record mode must be "I"
Last Update	

ICS0995E	**CCNA FIELD DOES NOT CONTAIN THE SAME VALUE AS THAT A OF THE HEADER**
Region	ALL
Form	ANY
Field	CCNA
Description	The IC's ID (CCNA field) in the record is different from the one that

	appears in the header record
Last Update	

ICS0996E	**SUPP FIELD VALUE MUST BE A 1, 2, 3, OR 4 WHEN RECORD MODE IS "C"**
Region	ALL
Form	ASR
Field	SUP
Description	Any change or correction request must have a "S" record with record mode (REC MODE) of "C" and a value of 1, 2, 3, or 4 in the supplement (SUP) field
Last Update	

ICS0998E	**SUPP FAILED**
Region	ALL
Form	NA
Field	NA
Description	The CCNA on the record does not match the CCNA in the data base
Last Update	

ICS0999E	**RESEND FAILED**
Region	ALL
Form	NA
Field	NA
Description	The CCNA on the record does not match the CCNA is the data base.
Last Update	

ICS1000E	**#RECS FIELD IN HEADER RECORD IS INVALID, PROCESS STOP FOR THIS FILE (BATCH)**
Region	ALL
Form	NA
Field	#RECS (HEADER RECORD)
Description	The number of records (#RECS) field contains non –numeric characters
Last Update	

ICS1000E	**#RECS FIELD IN HEADER RECORD IS INVALID, MESSAGE PROCESS STOPPED FOR THIS FILE (REAL-TIME INPUT)**
Region	ALL
Form	NA
Field	#RECS (HEADER RECORD)
Description	The number of records (#RECS) field contains non –numeric characters
Last Update	

ICS1005E	**#REQS FIELD IN HEADER RECORD IS INVALID, PROCESS STOP FOR THIS FILE (BATCH)**
Region	ALL
Form	NA
Field	#REQS (HEADER RECORD)
Description	The number of records (#REQS) field contains non –numeric characters

Last Update	

ICS1005E	**#REQS FIELD IN HEADER RECORD IS INVALID, MESSAGE PROCESS STOPPED FOR THIS FILE (REAL-TIME INPUT)**
Region	ALL
Form	NA
Field	#REQS (HEADER RECORD)
Description	The number of records (#REQS) field contains non −numeric characters
Last Update	

ICS1006E	**ASR VER FIELD IN HEADER RECORD IS INVALID, REQUEST PROCESSING STOPPED (REAL-TIME INPUT)**
Region	ALL
Form	NA
Field	VER (ASR HEADER)
Description	The version field of the ASR header is invalid
Last Update	
ICS1012E	**ADD FAILED**
Region	ALL
Form	NA
Field	NA
Description	The ICSC is invalid or not found in ICSC control cards
Last Update	

ICS1013E	**SUPP FAILED**
Region	ALL
Form	NA
Field	NA
Description	The ICSC is invalid or not found in ICSC control cards
Last Update	

ICS1014E	**RESEND FAILED**
Region	ALL
Form	NA
Field	NA
Description	The ICSC is invalid or not found in the ICSC control cards
Last Update	

ICS1015E	**REFNUM DOES NOT EXIST − REGIONAL RECORD REJECTED**
Region	ALL
Form	ANY
Field	REFNUM
Description	The REFNUM does not exist for this ASR in the system
Last Update	

ICS1016E	**NO OEC_ICSC FOUND − NO F40 RECORD SENT CONTAINING MATCHING ICSC**
Region	ALL
Form	NA
Field	NA
Description	We are processing an intended OEC and no F40 record was sent

	containing our matching OEC_ICSC
Last Update	

ICS1017E	**F40 RECORDS FOUND – NON MULITEC REQUEST, HOWEVER F40 RECORDS FOUND**
Region	ALL
Form	NA
Field	NA
Description	We are processing a non multi ASR and F40 records are being sent with the request
Last Update	

ICS1018E	**INVALID ASC- ASC EC VALUE ON ASR RECORD DOES NOT MATCH THAT ON F40A**
Region	ALL
Form	ASR
Field	ASC_EC
Description	The ASC_EC field on the on the "S" record does not match the ASC_EC field on the F40A record
Last Update	

ICS1019E	**DUPLICATE ICSC – F40 RECORD HAS DUPLICATE ICSC VALUES**
Region	ALL
Form	NA
Field	NA
Description	In processing an F40 record, it was discovered that duplicate ICSC values exist
Last Update	

ICS1020E	**NATIONAL ASR RECORD NOT PRESENT**
Region	ALL
Form	NA
Field	NA
Description	The ECI National ASR Record is missing; request is rejected
Last Update	

ICS1021E	**RECORD NOT PROCESSED, THE ASSOCIATED ASR RECORD WAS REJECTED**
Region	ALL
Form	NA
Field	NA
Description	The "S" record associated with this Application Record was rejected, therefore, this record was not process
Last Update	

ICS1022E	**RECORD NOT PROCESSED. THE REFNUM WAS OUT OF SEQUENCE**
Region	ALL

Form	NA
Field	NA
Description	The record was not processed. The REFNUM was out of sequence.
Last Update	

ICS1023E	**RECORD NOT PROCESSED. The VCNUM OR UREF WAS OUT OF SEQUENCE**
Region	ALL
Form	NA
Field	NA
Description	The record was not processed. The VCNUM or UREF was out of sequence.
Last Update	

ICS1025E	**ASR REJECTED – FLEX FATAL ERROR DETECTED**
Region	ALL
Form	ANY
Field	ANY
Description	The ASR was rejected by our ordering system (ARIS) because one or more fatal errors were found on subsequent records for this ASR
Last Update	

ICS1026E	**INCORRECT NUMBER OF UNIT TERMINATION POINTS PROVIDED**
Region	ALL
Form	EVC
Field	NUT
Description	The Number of UNI Termination (NUT) does not match the number of F47A records received
Last Update	

ICS1028E	**INVALID SERVICE TYPE FOR ETHERNET VIRTUAL CONNECTION SERVICE**
Region	ALL
Form	ASR
Field	EVCI
Description	The EVCI field is populated for an ASR with a REQTYP value other than "E", "S"
Last Update	

ICS1029E	**INVALID EVCI FOR ETHERNET VIRTUAL CONNECTION SERVICE**
Region	ALL
Form	ASR
Field	EVCI
Description	An ASR with a REQTYP of "S" was received with the EVCI field populated with a value other than "A" or blank or a REQTYP of "E" was received with the EVCI field populated with a value other than "B" or blank.
Last Update	

ICS1030E	**INVALID RECORD COMBINATION FOR ETHERNET VIRTUAL CONNECTION SERVICE**
Region	ALL
Form	NA
Field	NA
Description	ASR contains either a Transport (REC_TYP = "P" with an EVCI = "A" or an End User Special record (REC_TYP = "J") together with an EVC record (REC_TYP = F47A)
Last Update	

ICS1031E	**SUBMISSION OF EVC DATA REQUIRES THE EVCI FIELD BE POPULATED**
Region	ALL
Form	ASR
Field	EVCI
Description	ASRs containing an EVC record (REQ_TYP = F47A) but the EVCI field on the ASR (REC_TYPE = S) is not populated
Last Update	

ICS1032E	**INVALID CHANGE TO EVCI**
Region	ALL
Form	NA
Field	NA
Description	EVCI value may not be changed for the life of the ASR, except from a "B" to a blank
Last Update	

ICS1033E	**EVCNUM VALUE IS INVALID**
Region	ALL
Form	EVC
Field	EVCNUM
Description	EVCNUM contains an invalid value. The only valid value is 0001
Last Update	

ICS1034E	**ASR REJECTED – NO F47A RECORD FOUND FOR EVC SERVICE**
Region	ALL
Form	NA
Field	NA
Description	EVCI was populated but no F47A record was found for this request
Last Update	

ICS1035E	**SUPP FAILED – NO F47A RECORD FOUND FOR EXISTING UREF(S) ON EVC REQUEST**
Region	ALL
Form	EVC
Field	UREF, UACT
Description	A supp was received that committed a previously sent UREF that had

	not yet been cancelled
Last Update	

ICS1040E	**NATIONAL CIRCUIT LEVEL RECORD REFNUM XXXX WITHOUT CORRESPONDING RECORD**
Region	ALL
Form	NA
Field	NA
Description	The corresponding record, service specific or ACI/MSL, is missing for REFNUM XXXX of the ECI National Circuit Level Record which is rejected
Last Update	

ICS1279E	**WHEN CHANGING ASR TO MULTI EC IN ACTIVE SUPP STATUS, ASC EC MUST = ICSC**
Region	ALL
Form	ASR
Field	ASC_EC
Description	User attempted to change a non Multi EC ASR to a Multi EC ASR with the ASC_EC value not equaling the ICSC value
Last Update	

ICS1681E	**RTR MUST HAVE VALUE: F, N OR S**
Region	ALL
Form	ASR
Field	RTR
Description	User attempted to use valid entries of P and T; which will not be supported
Last Update	8/15/18

ICS1719E	**QNAI NOT VALID WITHOUT ACI OR ARI DATA WHEN QTY GREATER THAN 1**
Region	ALL
Form	ASR
Field	AFO, REQYTP
Description	When position 1 of AFO is blank, or REQTYP is not "R" and QTY is greater than 1, QNAI is not valid.
Last Update	

ICS1726E	**FOR NAI, POS 3 OF AFO MUST BE "Y" AND QNAI POPULATED**
Region	ALL
Form	ASR
Field	AFO
Description	AFO position 3 and QNAI must be populated for NAI data to be applicable.
Last Update	

ICS1747E	**SCREEN NOT VALID FOR REQTYP OR QSA MUST BE GREATER THAN 0**
Region	ALL
Form	

Field	
Description	Service Address Location Information is not valid: • When QSA is blank or 0 • For REQTYP "M" or "L" • For REQTYP "A", when NSL is 0
Last Update	

ICS1831E	**EVCI VALID VALUES ARE: A, B OR BLANK (REQTYP S), B OR BLANK (REQTYP E)**
Region	ALL
Form	ASR
Field	EVCI
Description	EVCI indicates Ethernet Virtual Connection: REQTYP 'S' with EVCI of 'A' indicates a standalone EVC. REQTYP 'E' or 'S' with EVCI of 'B' indicates a combination port and EVC order. Correct the EVCI value
Last Update	9/20/10

ICS1888E	**ASR REJECTED: INVALID CHANGE TO EVCI**
Region	ALL
Form	ASR
Field	EVCI
Description	EVCI field cannot be changed. Restore previous value of EVCI field
Last Update	9/20/10

ICS1890E	**EVCI = "A" IS ONLY VLAID FOR REQTYP "S"**
Region	ALL
Form	ASR
Field	EVCI
Description	Valid values of EVCI are 'A', 'B' or blank but EVCI = 'A' valid for REQTYP 'S' only. Correct the EVCI value.
Last Update	9/20/10

ICS5786E	**FIELD CANNOT BE CHANGED ON A SUPP 2**
Region	ALL
Form	ASR
Field	SUP
Description	When requesting a Due Date Change, SUP field on the ASR form = "2" only the following fields can be changed: DDD, EXP, FDT, ASR REMARKS, Service REMARKS fields.
Last Update	3/15/08

ICS7001E	**PRODUCT CAN NOT BE REQUESTED VIA THIS ORDERING TOOL**
Region	MIDWEST
Form	NA
Field	NA

Description	CLEC ASR request can no longer be sent via TELIS. CONNECT DIRECT ASRs can no longer be sent.
Last Update	

ICS7002E	**RTR IS A REQUIRED FIELD – VALID ENTRIES ARE N, F, S OR NUMERIC**
Region	SOUTHWEST, WEST
Form	ASR
Field	RTR
Description	The RTR field has a value that is not supported
Last Update	3/21/09

ICS7006E	**ICSC CODE INVALID FOR THIS EXACT DATA BASE**
Region	SOUTHWEST, WEST
Form	ASR
Field	ICSC
Description	ICSC code must be the correct value for the ASR ordering system (EXACT data base) that is receiving the ASR
Last Update	

ICS7007E	**ASR SENT TO WRONG DATA BASE LOCATION**
Region	SOUTHWEST, WEST
Form	ASR
Field	ICSC
Description	Based on the LATA for the ACTL or Primary location this request has been directed to the incorrect provider's data base. (Usually the ICSC code is incorrect for this error based on the LATA of the ACTL or primary location is in)
Last Update	

ICS7008E	**LTP CAN ONLY EQUAL BLANK, N OR F ON REQUEST TYPE OF L**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	LTP
Description	AT&T does not support the ordering of the transport facility on a combination ASR when ordering LINK services (REQTYP position 1 = "L")
Last Update	

ICS7010E	**GETO W IS THE ONLY ALLOWABLE AT&T OPTION**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	GETO
Description	The Value of "W" is the only options AT&T supports.

Last Update	9/18/10

ICS7011E	**IWBAN ENTRY OF BLANK OR "E" ARE PROHIBITED WHEN GETO IS POPULATED**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	IWBAN
Description	IWBAN field must be populated with a valid billing account number when the GETO field is populated.
Last Update	3/10/07

ICS7012E	**TGTYP VALUE OF "H" IS NOT VALID IN AT&T (*REGION)* IF TRFTYP-ORIG NOT=E9**
Region	WEST
Form	TRUNKING
Field	TGTYP
Description	AT&T does not support the trunk group type of "H" when ordering originating trunks for E911 service
Last Update	

ICS7013E	**A TGTYP VALUE OF "H" IS NOT SUPPORTED BY AT&T (*Region)***
Region	MIDWEST, SOUTHWEST
Form	TRUNKING
Field	TGTYP
Description	AT&T does not support the trunk group type of "H".
Last Update	

ICS7014E	**A VALID DRC CODE IS REQUIRED WHEN THE RTR = S OR 1-10**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	DRC
Description	DRC is required when the RTR is populated. The DRC cannot be blank or equal FAX, CPC or DLR.
Last Update	

ICS7015E	**NC/NCI/SECNCI NOT FOUND IN DATABASE**
Region	MIDWEST, SOUTHWEST, WEST
Form	ANY FORM THAT CONTAINS THE NC, NCI, SECNCI FIELD
Field	NC, NCI, SECNCI
Description	The NC, NCI, SECNCI combination was found not to be a valid combination in the ordering system.
Last Update	

ICS7016E	**NC/NCI/SECNCI COMBINATION IS NOT VALID FOR NEW ACTIVITY**
Region	MIDWEST, SOUTHWEST, WEST
Form	ANY FORM THAT CONTAINS THE NC, NCI, SECNCI FIELDS
Field	NC, NCI, SECNCI
Description	This NC, NCI, SECNCI combination has been grandfathered for "N" activity.
Last Update	

ICS7018E	**THE RTR OF S AND 1-10 ARE NOT VALID FOR D ACTIVITY, USE F OR N**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	RTR
Description	Requests for DLR information is not supported on disconnect activity. Resubmit this request with an RTR value of either "F" or "N"
Last Update	3/21/09

ICS7020E	**AT&T DOES NOT OFFER AT THIS TIME** **Note: There are 3 instances where this error is utilized, as shown below.**
Region	ALL
Form	ETHERNET VIRTUAL CONNECTION
Field	MULTIPLE
Description	AT&T does not support the following attributes, L2CP, , LOS, PBIT, DSCP, TOS, S-VLAN ID, R/L, first occurrence of the CE-VLAN field (positions 5-8 only) and the 13 new occurrences of the CE-VLAN field

ICS7020E	**(Continued)**
Region	All
Form	Transport, Additional Circuit Information, End User
Field	BI
Description	When the BI field is populated, the ASR will not be accepted

ICS7020E	**(Continued)**
Region	All
Form	EVC
Field	VACT
Description	When the VACT field is populated, the ASR will not be accepted
Last Update	9/15/12

ICS7020EA	**AT&T DOES NOT OFFER AT THIS TIME**
Region	ALL
Form	ASR
Field	LAG
Description	When the LAG is populated on the ASR screen, this message will occur
Last Update	3/16/13

ICS7020EA	**AT&T DOES NOT OFFER AT THIS TIME**
Region	ALL
Form	EVC
Field	SVP
Description	When the SVP is populated on the EVC screen, this message will occur
Last Update	3/16/13

ICS7021E	**DESIRED DATE DUE MUST BE VALID DAY, MONTH AND YEAR**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	DDD
Description	The desired due date must be a valid date comprised of the following: • A two digit Day – valid values of 01 through 31 • A two digit month – valid values of 01 through 12 • A two century - valid value of 20 • A two digit year (current year, based on the year the ASR is sent) plus or minus 1 year
Last Update	3/10/07

ICS7022E	**DDD CAN NOT EXCEED 180 DAYS-PLEASE CORRECT**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	DDD
Description	The DDD cannot exceed 180 days from the receipt of the ASR as stated in the tariff. This does not change the due date process defined in the ASOG.
Last Update	3/10/07

ICS7023E	**BAN REQUIRED**
Region	ALL (IXC and Wireless Customers only)
Form	MIDWEST, SOUTHWEST, WEST
Field	BAN
Description	AT&T requires the customer to provide the BAN information as defined in the ASOG. Sending in no data in the BAN field is not an acceptable entry. Therefore the ASR will not be accepted when : • BAN field contains no data (blanks) and • The Company Code (CC) field is blank Provide the correct BAN information and re-transmit the ASR *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and Wireless customers.*
Last Update	9/15/07

ICS7024E	**SECNCI NOT VALID FOR THIS NC CODE**
Region	MIDWEST, SOUTHWEST, WEST (CLEC Customers only)
Form	End User Special Access or Transport
Field	SECNCI
Description	SECNCI information is not required when ordering multiplexed Digital high Capacity Services (HC1 and HC3). Therefore the ASR will not be accepted when: • The Company Code (CC field on the ASR form) is populated • The Requisition type (REQTYP, position 1 on the ASR form) is either "S" or "E" • The activity (ACT field on the ASR form) is "N" or "C" • The Network channel code (NC field on the Transport and End

	User Special Access form) is HC+M or HF+M (+ = any character) • The Secondary Network Channel Interface (SECNCI on the Transport form) is populated Remove the SECNCI information and re-transmit the ASR *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is populated which indicates a CLEC customer.*
Last Update	9/15/07

ICS7050E	**INCORRECTLY FORMATTED CFA**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The value in the CFA or the SCFA field is formatted incorrectly
Last Update	

ICS7051E	**CFA FACILITY DESIGNATION (FACDESG) IS NOT VALID**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The value in the FACDESG element of the CFA or the SCFA is invalid
Last Update	

ICS7052E	**CFA FACILITY TYPE (FACTYP) IS NOT VALID**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The value in the FACTYP element of the CFA or the SCFA is invalid
Last Update	

ICS7053E	**CFA CHANNEL (CHAN) IS NOT VAILD**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The value in the CHAN element of the CFA or the SCFA is invalid
Last Update	

ICS7054E	**CFA LOCATION A CLLI (LOC A) IS NOT VALID**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The value in the location A element of the CFA or SCFA is invalid
Last Update	

ICS7055E	**CFA LOCATION Z CLLI (LOC Z) IS NOT VALID**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The value in the location Z element of the CFA or SCFA is invalid
Last Update	

ICS7056E	**SYSTEM ERROR WHILE PROCESS CFA, PLEASE CONTACT SUPPORT**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	NA
Description	An undetermined error occurred while performing a CFA validation
Last Update	

ICS7057E	**CFA NOT FOUND**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The CFA or SCFA was not found in the provisioning system
Last Update	

ICS7058E	**CFA CHAN UNAVAIL**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	CFA or SCFA
Description	The CHAN provided is not available for the CFA or the SCFA provided
Last Update	

ICS7059E	**SERVICE ADDRESS NOT FOUND**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	ADDRESS FIELDS
Description	The service address provided was not found in the address system
Last Update	

ICS7060E	**AN EXACT ADDRESS MATCH NOT FOUND**
Region	MIDWEST, SOUTHWEST, WEST
UOM	PRE-VALIDATION
Field	ADDRESS FIELDS
Description	An exact match of the address provided was not found in the address system
Last Update	

ICS7075E	***ASR CANNOT CONTAIN BOTH CFA & CCEA***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access, Additional Circuit
Field	CCEA and CFA
Description	When ordering Co-Location or riding services both the CFA and the CCEA information cannot be populated. The ASR will not be accepted if both the CFA and the CCEA fields are populated. Correct the ASR by determining which of the two fields are necessary for the service being ordered. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*

Last Update	3/15/08

ICS7076E	***SPOT FIELD REQUIRED WHEN SECLOC IS CUSTOMER PREM (E)***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Ring, Additional Ring
Field	SPOT (Secondary Location)
Description	When the secondary location is a customer's node the SPOT field associated with the secondary location is required to be populated with a CLLI code for the point of termination. Therefore, the ASR will not be accepted when the SPOT field is blank. The SPOT field is required under the following conditions: • The REQTYP, position 1 on the ASR form, is "R" • The ACT field on the ASR form is "N" or "C" or the ACT field is "C" and the SEGACT field on the Ring or Additional Ring form is "C" or "N". • The SECLOC field, position 1 is "E" which indicates a customer node *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7077E	***FNI MUST BE POPULATED FOR THIS SERVICE***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	FNI
Description	When ordering AT&T's Dedicated SONET Ring Service, OCN point to point service, DS1 or DS3 service riding SONET, MON ring and sub-tending services riding MON ring the FNI field must be populated. When ordering the above services, the first position of the REQTYP will be "E", "R" or "S". Following are the conditions that are excluded from this validation: • When the SPEC field contains any of the following codes: OPTEB, OPTES, CSME15, CSME2C, WAVMAN, DECMAN, EOSCKT, UNB in the first 3 positions, TWO in the first 3 positions. • The NC is any of the following codes: OB*R, OF*R, OG*R. (* can be any value) • Disconnection activity Correct the ASR to provide the appropriate FNI information. *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7078E	***CFA ACTL CLLI MUST MATCH ACTL CLLI ON ASR***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport
Field	CFA
Description	The ACTL CLLI on the ASR form must match either the A location or the Z location CLLI codes when ordering multiplexer cross connects. The following criteria is when we will expect the match to occur: • The REQTYP, position 1 on the ASR form, is "S" • The ACT field on the ASR form is "N", "C", "M" or "T" • The LTP field is "N" or blank • Midwest additional requirements: o The first two positions of the NC code equal "HC", "HD", "HF", "HG", "HS", "XA", "XB", "XG", "XH", "XD", "XC" • See exceptions below for Midwest o The following NC codes are excluded from the above error: "HS--", "XAAC", XAHC", "XBAC", "XBHC", "XGAC", "XGHC", "XHAC", "XHHC", "XCAC", XCHC" or "XDAC" *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7079E	***CFA REQUIRED FOR THIS NCI, WHEN NC = HC++***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport and End User
Field	NCI
Description	CFA information is required when ordering DS1 service when the first two positions of the NC code are "HC" and the NCI is equal to the ones listed below. CFA is required when: • The REQTYP, position 1 on the ASR form is "E" or "S" and • The NC code, position 1-2 is "HC" and • The NCI is "04DS6.44", "02SOF.B" , "04SOF.C", "02SOF.E", "04SOF.E", O4ST6.C"or "04QB6.33" Correct the ASR to provide the CFA information *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7080E	***DS1 CIRCUIT CANNOT RIDE DS1 CFA***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport
Field	CFA
Description	When ordering a DS1 circuit the CFA information on the ASR cannot

	be at a DS1 level. Therefore the ASR will <u>not</u> be accepted if the following situation exist: • The REQTYP, position 1 on the ASR form is "S" • The NC code, position 1-2 on the transport form is "HC" • The CFA on the transport form is at a DS1 level *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7081E	***WHEN SPEC FIELD INDICATES DISASTER REMAP, PRILOC MUST BE A CUST PREM (E)***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Ring, Additional Ring
Field	SECLOC
Description	When ordering disaster remap the PRILOC <u>must</u> be a customer premise. Therefore the PRILOC field on the Ring or additional ring form must contain an "E" in the first position to indicate a customer premise in the following situations: • The REQTYP, position 1 on the ASR form, is "R" • The ACT field on the ASR form is "N" or "C" or the ACT field is "C" and the SEGACT field on the Ring or Additional Ring form is "C" or "N". • The SPEC field contains "SRRDRS" on the Ring form or the SPEC field contains "SNRADDL" on the Additional Ring form. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7082E	***CENTREX NC CODES REQUIRE DATA IN THE CTX-TEL FIELD***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access
Field	Centrex Telephone Number (CTX TEL)
Description	When ordering Centrex service the Centrex telephone must be populated. The Centrex telephone number must be provided in the following situations: • The REQTYP, position 1 on the ASR form, is "S", "E" • The ACT field on the ASR form is not equal to "D" • The NC code indicates Centrex service

	Correct the ASR to provide the Centrex telephone number *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7083E	***CLLI IS REQUIRED IN PRILOC WHEN ORDERING DSRS REGENERATOR***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Ring, Additional Ring
Field	PRILOC
Description	When ordering a dedicated SONET ring service with a regenerator the PRILOC information must contain a CLLI code for the central office in the following condition: • The REQTYP, position 1 on the ASR form, is "R" • The ACT field on the ASR form is "N" • The SPEC code is "NBLREGN" or the NCI code positions 1 through 5 = "02RGF" Correct the ASR to provide the correct CLLI information in the PRILOC field. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers*
Last Update	3/15/08

ICS7085E	***DS0 CIRCUIT CANNOT RIDE DS3 CFA***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access
Field	CFA
Description	When ordering a DSO service (voice grade, metallic, telegraph) the CFA provided cannot be at a DS3 level. The CFA cannot be at a DS3 level when • The REQTYP, position 1 on the ASR form is "S", or "E" • The ACT field on the ASR form is "N" • The NC code indicates a DSO service Correct the ASR to provide the appropriate level of CFA information. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7086E	***C.NPANXX FIELD MUST BE POPULATED***
Region	MIDWEST, SOUTHWEST, WEST (Wireless Customers only)

Form	Translation Questionnaire – Interconnection/STP Translations Routing
Field	C.NPANXX
Description	Wireless service trunks ordered new as originating, two-way or land to mobile requires at least one NPA/NXX to be provided. At least one C.NPANXX field must be populated when: • If the REQTYP, position 1 on the ASR form is "M" • The ACT field on the ASR form is "N" • The first position of the TQ field is "W", "C" or "X" • The TTT field is "1", "3" or "9" Correct the ASR to provide the NPA/NXX information in the C.NPA/NXX field. *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7087E	***IWBAN IS IN INVALID FORMAT, PLEASE CORRECT***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	IWBAN
Description	The information provided in the IWBAN field should indicate a proper BAN for AT&T. If the data provided contains any of the following data the BAN is considered to be invalid: • IWBAN field is populated with all zeros (0s) or nines (9s) • IWBAN field data is less than 10 characters • The first position of the IWBAN field contains a numeric value Correct the ASR to provide a valid BAN in the IWBAN field. Note: If the ASR reflects a jointly provided service the above information will only apply when the IWBAN is to reflect an AT&T BAN. *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers*
Last Update	3/15/08

ICS7088E	***VTA REQUIRED WHEN PROJECT = "NOMONEYDOWN"***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	VTA
Description	When participating in the "No Money Down" promotion VTA information is required. VTA information is required when:

	• The REQTYP, position 1 on the ASR form is "S" or "E" • The Project field on the ASR form contains "NOMONEYDOWN" Correct the ASR to provide the appropriate VTA information. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7089E	***REQTYP M INVALID WHEN SPEC EQUALS "RCADS1"***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	SPEC
Description	When ordering Reciprocal Compensation Agreement for DS1 Service the SPEC code must = "RCADS1" and the first position of the REQTYP, must = "S". *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7090E	***JACK CODE MUST BE EITHER 3 OR 5 CHARACTERS***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Service Address Location Information, Additional Circuit
Field	JK CODE
Description	When ordering a jack code it must be either 3 or 5 positions in length.
Last Update	3/15/08

ICS7091E	***WST REQUIRED FOR WIRELESS SERVICE-MUST BE F, G, H, L***
Region	MIDWEST, SOUTHWEST, WEST (Wireless Customers only)
Form	ASR
Field	WST
Description	When ordering switched wireless service the WST field must be populated with an "F", "G" or "H". The WST field must contain an "F", "G" "H" or "L" when: • The REQTYP, position 1 on the ASR form is "M" • The CIC field on the trunking for equals "0698" Correct the ASR to provide the appropriate WST information. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7092E	***ASR CANNOT CONTAIN BOTH SCFA & SCCEA***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access, Additional Circuit
Field	SCCEA and SCFA
Description	When ordering Co-Location or riding services both the SCFA and the SCCEA information cannot be populated. The ASR will not be accepted if both the SCFA and the SCCEA fields are populated. Correct the ASR by determining which of the two fields are necessary for the service being ordered. *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7093E	***INVALID LTP WHEN NC1 IS POPULATED***
	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	LTP
Description	When ordering Switched trunks and facilities on a combination ASR the LTP value must reflect the correct entry. LTP values of "N" or Blank are not acceptable values. Correct the ASR to add the appropriate LTP value *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7094E	***INVALID NC CODE FOR GIGAMAN SERVICE***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access
Field	NC
Description	The GIGAMAN product line has new NC codes and this edit is to prevent ordering any new GIGAMAN service with the outdated codes. Therefore the ASR will not be accepted in the following situation: • The REQTYP, position 1 on the ASR form is "S" or "E" • The ACT field on the ASR form is "N" • The NC code, positions 1 and 2 equal "BF" Correct the ASR to add the appropriate NC code *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*

Last Update	3/15/08

ICS7095E	***INVALID SONNET CFA FACILITY TYPE-CORRECT FROM STS+ OR VT1+ TO OC+***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access, Additional Circuit
Field	CFA on the transport and Additional Circuit form CFA (PRILOC) on the End User Special Access from *Note: In the description the term CFA will be used to represent the CFA and CFA (PRILOC) fields*
Description	When the information in the CFA field reflects a SONET CFA the facility type segment cannot begin with "ST" or "VT". The correct information for the facility type should reflect "OC+", where the + represents the SONET level, e.g. OC48. The CFA facility segment must be "OC+" when the CFA reflects a SONET service in the following situations: • The REQTYP, position 1 on the ASR form is "S" or "E" • The ACT field on the ASR form is "N" • See exception below <u>Exception for the Southwest and West Regions:</u> • A facility segment equal to "ST01" is valid and will not error Correct the ASR to reflect the appropriate CFA facility type, OC+. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7096E	***INVALID SONNET SCFA FACILITY TYPE-CORRECT FROM STS+ OR VT1+ TO OC+***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport, End User Special Access, Additional Circuit
Field	SCFA on the transport and Additional Circuit form SCFA (SECLOC) on the End User Special Access form *Note: In the description the term SCFA will be used to represent the SCFA and SCFA (PRILOC) fields*
Description	When the information in the SCFA field reflects a SONET SCFA the facility type segment cannot begin with "ST" or "VT". The correct information for the facility type should reflect "OC+", where the + represents the SONET level, e.g. OC48. The SCFA facility segment must be "OC+" when the CFA reflects a SONET service in the following situations: • The REQTYP, position 1 on the ASR form is "S" or "E" • The ACT field on the ASR form is "N" • See exception below <u>Exception for the Southwest and West Regions:</u>

	• A facility segment equal to "ST01" is valid and will not error Correct the ASR to reflect the appropriate SCFA facility type, OC+. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7098E	***VTA FOR FAST SERVICE MUST BE 36***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	VTA
Description	When participating in the Federal Government Special Pricing Plan (FAST) the VTA information must reflect 36 months. VTA information is required when: • The REQTYP, position 1 on the ASR form is "S" or "E" • The ACT field on the ASR form is "N" • The Project field on the ASR form contains "FAST" • The PIU = "100" Correct the ASR to provide the appropriate VTA information. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7101E	***FNI MUST BEGIN WITH N WHEN ORDERING THIS SERVICE***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	FNI (Position 1)
Description	When ordering AT&T's Dedicated SONET Ring Service, OCN point to point service, DS1 or DS3 service riding SONET first position of the FNI field must be populated with an "N". When ordering the above services the first position of the REQTYP will be "E", "R" or "S". Correct the ASR to provide the appropriate FNI information for the service being ordered. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7102E	***FNI MUST BEGIN WITH W WHEN ORDERING THIS SERVICE***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR

Field	FNI (Position 1)
Description	When ordering AT&T's MON ring and sub-tending services riding MON ring first position of the FNI field must be populated with a "W". When ordering the above services the first position of the REQTYP will be "E", "R" or "S". Correct the ASR to provide the appropriate FNI information for the service being ordered. *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7103E	***INVALID FNI FORMAT – PLEASE CORRECT***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	FNI
Description	When providing FNI information the only valid entries allowed are an "N" or a fiber network identification code. Populating the field with an "E" or "NA" are not acceptable values. Correct the ASR to provide the correct FNI information. *Note: This edit applies only when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7105E	***LTP REQUIRED FOR SWITCHED FACILITY WHEN SECLOC CLLI IS 11 CHARACTERS***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	LTP
Description	When ordering a switched facility the correct LTP information is required. A valid LTP entry is required when: • The REQTYP, position 1 on the ASR form = "S" • The NC code on the transport form = "HC+D" or "HC+H" ; where the "+" represents any valid option • The SECLOC field on the transport form contains a valid CLLI code preceded by a "C" • See exception below Exception for the Midwest region: When the Spec code indicates a wireless service provider or a 911 facility. Correct the ASR to reflect the correct LTP code for the switched

	facility. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7106E	***SPEC "NSDWRG" – CANNOT EXPEDITE WHEN DIVERSITY INVOLVED***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	ASR
Field	EXP
Description	When ordering deregulated expedited inside wiring (SPEC field on the ASR form is "NSDWRG") and special routing (SR field on the service specific form) the expedite field (EXP) on the ASR cannot be populated. Correct the ASR to either remove the "Y" in the EXP field or remove the SR data. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers.*
Last Update	3/15/08

ICS7107E	***SPEC 'NSDWRG' REQUIRES GETO OF "W" AT ENDUSER LOCATION***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	EUSA, Transport, MSL
Field	GETO
Description	When ordering deregulated expedited inside wiring (SPEC field on the ASR form is "NSDWRG") an associated GETO field with the end user location must contain a "W". Correct the ASR to show at least one of the locations GETO field to be a "W". *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers*
Last Update	3/15/08

ICS7108E	***SPEC 'NSDWRG' REQUIRES GETO OF "W" AT ENDUSER LOCATION***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	EUSA, Transport, MSL
Field	GETO
Description	When ordering deregulated expedited inside wiring (SPEC field on the ASR form is "NSDWRG") at least one location must be an end

	user location. (Reflected by an "E" in the first position of either the PRILOC or SECLOC field on the appropriate form) Correct the ASR to show at least one of the locations GETO field to be a "W". *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers*
Last Update	3/15/08

ICS7109E	***APS SERVICE IS GRANDFATHERED – ACT OF "N" OR "T" NOT ALLOWED***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	EUSA, Transport
Field	NC
Description	Automatic protection switching (Automatic loop transfer) service has been discontinued and is no longer a valid offering. Any new request (ACT field on the ASR form = "N" or "T") for this service will not be accepted. Disconnect activity is the only type of ASR request that will be accepted. The ASR will <u>not</u> be accepted in the following situation: • The REQTYP, position 1 on the ASR form is "S" or "E • The ACT field on the ASR form is "N" or "T" • The NC code reflects automatic protection switching ("HC+P" where the + = any option) Correct the ASR to reflect an NC code to one that is offered by AT&T. *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers*
Last Update	3/15/08

ICS7110E	***SECLOC MUST EQUAL "E" WHEN QSA IS POPULATED***
Region	MIDWEST, SOUTHWEST, WEST (IXC and Wireless Customers only)
Form	Transport
Field	SECLOC
Description	When utilizing the service address location form (SALI) by populating the QSA field on the ASR form the first position of the SECLOC must = an "E". The only exception will be when the ACT field on the ASR form for is a "D" (Disconnect activity) *Note: This edit applies <u>only</u> when the company code (CC) field on the ASR form is blank. If the CC field is populated, this edit will not be applied since there is a different process in place for the non IXC and wireless customers*
Last Update	3/15/08

ICS7111E	**SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE**
Region	MIDWEST, SOUTHWEST, WEST
Form	TRANSPORT, END USER SPECIAL ACCESS
Field	SEI
Description	When ordering switched Ethernet service, the SEI field must be populated. Switched Ethernet service can be identified when the Spec field contains one of the following codes: OEMA++, OPTEBB, OPTEBC, OPTEBE, OPTEBF, OPTESB, OPTESC, OPTESE, OPTESF, OPTEEB, OPTEEC, OPTEEE, OPTEEF, CSME15, and CSME2C. Correct the ASR to populate the SEI field.
Last Update	9/21/19

ICS7112E	**SPEC DATA REQUIRED WHEN SEI IS POPULATED**
Region	MIDWEST, SOUTHWEST, WEST
Form	TRANSPORT, END USER SPECIAL ACCESS
Field	SPEC
Description	When ordering switched Ethernet service and the SEI field is populated the SPEC field must contain one of the following codes: OEMA++, OPTEBB, OPTEBC, OPTEBE, OPTEBF, OPTESB, OPTESC, OPTESE, OPTESF, OPTEEB, OPTEEC, OPTEEE, OPTEEF, CSME15, and CSME2C. Correct the ASR to add one of the above codes to the SPEC field on the ASR.
Last Update	9/21/19

ICS7114E	**ECCKT WITH SERVICE CODE OF VL NOT VALID ON ASR FORM. USE EVC FORM.**
Region	ALL
Form	ASR
Field	ECKKT
Description	If ASR ACT = D and ECKKT Service code = VL, then EVC form must be submitted.
Last Update	3/19/11

ICS7116E	**FATAL EDIT: RTR FIELD MUST BE N OR F FOR DISCONNECT ORDERS**
Region	Southeast
Form	ASR
Field	RTR, DRC
Description	When issue a disconnect ASR the RTR field cannot reflect a request for A DLR. The DRC field should be blank when issuing a disconnect ASR. Modify the RTR field to reflect an "F – Send FOC only", or "N – No response required". Remove any data that appears in the DRC field.
Last Update	Existing, added to document with version 9

ICS7117E	**FATAL EDIT: DUE DATE ON ORDER CAN NOT BE EARLIER THAN TODAY**
Region	Southeast
Form	ASR
Field	DDD
Description	An ASR request was received with a DDD that is earlier than today. Resubmit the ASR with a DDD that is not equal to today
Last Update	Existing, added to document with version 9

ICS7118E	**FATAL EDIT: USE WSR FOR WIRELESS SERVICE REQUESTS**
Region	Southeast
Form	ASR,
Field	WST
Description	When issuing a request for wireless service please us the WSR process. If the request is not for a wireless service then remove the data from the WST field and resubmit the ASR
Last Update	Existing, added to document with version 9

ICS7119E	**FATAL EDIT: ALTERNATE ACTL OPTION NOT CURRENTLY AVAILABLE ON RINGS**
Region	Southeast
Form	NAI
Field	ACFA, AFACTL
Description	Use of the ACFA and or the AFACTL fields on the network assignment information for is not permitted. Remove the data from these fields and resubmit the ASR
Last Update	Existing, added to document with version 9

ICS7122E	**FATAL EDIT: TELIS APP NO LONGER AVAIL. FOR INITIAL REQUESTS**
Region	Southeast
Form	ASR
Field	CNO
Description	TELIS application is no longer available for initial requests. Resubmit ASR via the common access front end (web application) contact account team for access.
Last Update	Existing, added to document with version 9

ICS7123E	**FATAL EDIT: MUXLOC MUST BE BLANK BASED ON SERVICE ORDERED**
Region	Southeast
Form	Service Specific Form
Field	MUXLOC
Description	Resubmit the ASR with the MUXLOC field blank. Refer to the MUXLOC

	customer education package. http://wholesale.att.com/ and search on MUXLOC
Last Update	Existing, added to document with version 9

ICS7124E	**FATAL EDIT: MUXLOC INCORRECTLY POPULATED BASED ON SERVICE ORDERED**
Region	Southeast
Form	Service Specific Form
Field	MUXLOC
Description	Resubmit the ASR with the correct MUXLOC information. Refer to the MUXLOC customer education package. http://wholesale.att.com/ and search on MUXLOC
Last Update	Existing, added to document with version 9

ICS7125E	**FATAL EDIT: MUXLOC INVALID DUE TO INCORRECTLY POPULATED CFA**
Region	Southeast
Form	Service Specific Form
Field	MUXLOC
Description	MUXLOC information is not valid either resubmit the ASR with the MUXLOC field blank or correct the CFA information. Refer to the MUXLOC customer education package. http://wholesale.att.com/ and search on MUXLOC
Last Update	Existing, added to document with version 9

ICS7126E	**FATAL EDIT: CFA IS NON-STANDARD FORMAT**
Region	Southeast
Form	Service Specific Form
Field	CFA
Description	The information contained in the CFA field does not correctly display a correctly formatted SONET CFA. Update the CFA information and resubmit. Refer to the MUXLOC customer education package. http://wholesale.att.com/ and search on MUXLOC
Last Update	Existing, added to document with version 9

ICS7127E	**FATAL EDIT: SCFA IS NON-STANDARD FORMAT**
Region	Southeast
Form	Service Specific Form
Field	SCFA
Description	Based on the entry in the SCFA either the MUXLOC field must be blank or a correctly formatted SCFA is required. Refer to the MUXLOC customer education package. http://wholesale.att.com/ and search on MUXLOC

Last Update	Existing, added to document with version 9

ICS7128E	**FATAL EDIT: ICFA1 - 4 IS NON-STANDARD FORMAT**
Region	Southeast
Form	NAI
Field	ICFA1-4
Description	Based on the entry in the ICFA1-4 either the MUXLOC field must be blank or a correctly formatted ICFA1-4 is required. Refer to the MUXLOC customer education package. http://wholesale.att.com/ and search on MUXLOC
Last Update	Existing, added to document with version 9

ICS7129E	**FATAL EDIT: ETHERNET VIRTUAL CONNECTION IS NOT SUPPORTED AT THIS TIME**
Region	Southeast
Form	ASR
Field	EVCI
Description	The use of the Ethernet Virtual Connection Form is not supported at this time. Resubmit the ASR with the EVCI field blank.
Last Update	Existing, added to document with version 9

ICS7131E	**FATAL EDIT:MAXIMUM SUPPS RECEIVED - CANCEL AND REISSUE PON**
Region	Southeast
Form	ASR
Field	SUP
Description	There can only be 98 Supplements issued on a single ASR. Cancel and reissue the ASR.
Last Update	Existing, added to document with version 9

ICS7132E	**FATAL EDIT: VIRTUAL CONCANTENATION IS NOT SUPPORTED AT THIS TIME**
Region	Southeast
Form	ASR
Field	AFO (Position 5)
Description	Virtual Concatenation is not supported at this time. Resubmit the ASR with position 5 of the AFO field blank.
Last Update	Existing, added to document with version 9

ICS7136E	**FATAL EDIT: SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE**
Region	Southeast
Form	TRANSPORT, END USER SPECIAL ACCESS
Field	SEI

Description	When ordering switched Ethernet service the SEI field must be populated. Switched Ethernet service can be identified when the SPEC field begins with ME
Last Update	Existing, added to document with version 9

ICS7137E	**FATAL EDIT: SPEC DATA REQUIRED WHEN SEI IS POPULATED**
Region	Southeast
Form	TRANSPORT, END USER SPECIAL ACCESS
Field	SPEC
Description	When ordering Switched Ethernet service and the SEI field is populated the SPEC field must be populated and begin with ME.
Last Update	Existing, added to document with version 9

ICS7139E	**FATAL EDIT: COMBO ASR NOT SUPPORTED FOR ETTCS**
Region	MIDWEST, SOUTHWEST, WEST
Form	ASR
Field	ACT, ACNA, SPEC, EVCI
Description	Combination ASR not allowed when all of the following are true: ACT= N; and SPEC 1 begins with "OPTE"; and ACNA or ACNA Parent = one of the following: "SBM", "PUL", "WCG", "MQS", "RKM". Issue a separate ASR for the UNI and a separate ASR for the EVC, where the EVCI value is "A"
Last Update	3/19/11

ICS7140E	**FATAL EDIT: COMBO ASR NOT SUPPORTED FOR RTP**
Region	All
Form	ASR, EVC
Field	ACT, Project, NC
Description	Combination ASR not allowed when ACT = N, PROJECT begins with "RTP", and NC on EVC form = "VLM-", "VLP-". Issue a separate ASR for the UNI and a separate ASR for the EVC, where the EVCI value is "A"
Last Update	3/19/11

ICS7141E	**FATAL EDIT: REQUIRED ASOG FIELDS MISSING (CITY, STATE, ZIP)**
Region	All
Form	SALI
Field	City, State, Zip

Description	If SASN is populated the CITY, STATE, and ZIP fields are required. Resubmit ASR with City, State, Zip populated
Last Update	3/17/12

ICS7142E	**FATAL EDIT: ASC-EC REQUIRED WHEN ICOL POPULATED**
Region	All
Form	ASR
Field	ASC-EC
Description	ASC-EC required when ICOL is populated on SALI form. Resubmit ASR with ASC-EC populated
Last Update	3/17/12

ICS7143E	**FATAL EDIT: SAPR, SASF, SASD, SATH, SASS PROHIBITED WHEN AFT = D AND SANO IS BLANK**
Region	All
Form	SALI
Field	SAPR, SASF, SASD, SATH, SASS
Description	When the AFT field is populated with a "D" for descriptive addresses, customers should only send the address fields SASN, CITY, STATE, and ZIP on the ASR. Resubmit ASR with SAPR, SASF, SASD, SATH, SASS blank
Last Update	3/17/12

ICS7144E	**FATAL EDIT: SAG ONLY ADDRESS – VERIFY IF NEW CONSTRUCTION**
Region	All
Form	SALI
Field	Address fields
Description	SAG only addresses will be considered valid for new construction only. Customers should verify if the site is new construction and if so resubmit with NCON = "Y".
Last Update	3/17/12

ICS7145E	**FATAL EDIT: ASC-EC REQUIRED WHEN OTC POPULATED**
Region	All
Form	ASR

Field	ASC-EC
Description	Field is required when OTC is populated on End User, Transport, Ring, Additional Ring Information, or Multipoint Service Legs Forms. Resubmit ASR with ASC-EC populated.
Last Update	3/17/12

ICS7146E	**FATAL EDIT: ATT DOES NOT SUPPORT AFT = "E"**
Region	All
Form	SALI
Field	AFT
Description	A value of "E" in this field is not supported by AT&T. Resubmit ASR with a different value.
Last Update	3/17/12

ICS7147E	**FATAL EDIT: ADDRESS NOT VALID FOR LATA, PLEASE VERIFY ICSC & REGION**
Region	All
Form	SALI
Field	Address fields
Description	Address does not appear for LATA populated. Verify ISCS and region and resubmit ASR
Last Update	3/17/12

ICS7148E	**FATAL EDIT: PRODUCT NOT ELIGIBLE AT ROUTE, REQUEST INVALID**
Region	West, Southwest,
Form	End User
Field	PRILOC, SECLOC
Description	Invalid route information. Resubmit ASR with valid information
Last Update	3/17/12

ICS7149E	**FATAL EDIT: DUE TO SYSTEM LIMITATIONS AT&T DOES NOT SUPT AAI GREATER THAN 60 CHARS**
Region	All
Form	SALI
Field	AAI
Description	Due to present system limitations, AT&T does not support population of more than 60 characters in the AAI field. Resubmit ASR with 60 characters or less in this field.

Last Update	3/17/12

ICS8447E	**PROFILE REQUIRED WHEN ORDERING PPCOS**
Region	All
Form	EVC
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	9/2010

ASOG49 Release Error Code Section – September 20th, 2014

EDIT	**ISC1852E**
EDIT Message	**SCREEN/RECORD IS NOT VALID WHEN SEI IS POPULATED**
Form	ASR, TRANSPORT, EUSA
Region	All regions
Type Change	NEW
Field	SEI
Description	If REQTYP1_1 is 'E' or 'S' and SEI is 'Y' and a Transport (REC_TYP = 'P' or EUSA (REC_TYP = 'J' record is submitted instead of the SES record (REC_TYP = 'L')
Last Update	9/20/14

EDIT	**ICS1853E**
EDIT Message	**SWITCHED ETHERNET SERVICE NOT VALID FOR REQTYP OR SEI IS NOT "Y"**
Form	ASR, TRANSPORT, EUSA
Region	ALL
Type Change	NEW
Field	SEI
Description	If REQTYP1_1 is not 'E' or 'S' and SEI is 'Y' and an SES record (REC_TYP = 'L') is submitted instead of a Transport (REC_TYP = 'P') or EUSA (REC_TYP = 'J') record
Last Update	9/20/14

EDIT	**ICS1701E**

EDIT Message	**SEI IS NOT VALID WHEN EVCI IS A**
Form	ASR
Region	ALL
Type Change	NEW
Field	SEI, EVCI
Description	If REQTYP1_1 is 'S' and EVCI = 'A' and SEI = 'Y'.
Last Update	9/20/14

EDIT	**ICS1854E**
EDIT Message	**CHANGING SEI NOT ALLOWED ONCE SERVICE SPECIFIC DATA HAS BEEN ADDED**
Form	ASR
Region	ALL
Type Change	NEW
Field	SEI
Description	If ASR was submitted and is re-submitted with a change to SEI from blank to 'Y' or 'Y' to blank
Last Update	

EDIT	**ICS7111E**
EDIT Message	**SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE** **Note: This replaces the current AT&T Southeast Region edit of - ICS7136E SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE. Edit is being expanded to all regions.**
Form	ASR
Region	ALL
Type Change	NEW/ REPLACES REGIONAL EDIT
Field	SEI
Description	
Last Update	9/20/14

EDIT	**ICS7111E**
EDIT Message	**SEI DATA REQUIRED FOR SWITCHED ETHERNET SERVICE** **Note: This replaces the current AT&T Southeast Region edit of - ICS7136E SEI DATA REQUIRED FOR SWITCHED**

	ETHERNET SERVICE. Edit is being expanded to all regions.
Form	ASR
Region	ALL
Type Change	NEW/ REPLACES REGIONAL EDIT
Field	SEI
Description	
Last Update	9/20/14

ASOG50 Release Error Code Section – March 21st, 2015

EDIT	**ICS1689E**
EDIT Message	**BI VALID ENTRIES: A OR Y**
Form	SES/ ACI
Region	ALL
Type Change	NEW
Field	BUNDLING INDICATOR – (BI)
Description	CONTENT VALIDATION OF BI FIELD
Last Update	3/20/15

EDIT	**ICS1857E**
EDIT Message	**SM VALID ENTRIES: D OR E**
Form	SES / ACI
Region	ALL
Type Change	NEW
Field	SYNCHRONOUS MODE – (SM)
Description	CONTENT VALIDATION OF SM FIELD
Last Update	3/20/15

EDIT	**ICS1863E**
EDIT Message	**L2CPP VALID ENTRIES: A THROUGH T EXCLUDING I AND O**
Form	SES /EUSA / TRANSPORT
Region	ALL
Type Change	NEW
Field	LAYER TWO CONTROL PROTOCOL PEERING – (L2CPP)
Description	CONTENT VALIDATION OF L2CPP
Last Update	3/20/15

EDIT	**ICS1859E**
EDIT Message	**UNI-MSFS / MSFS FIELD MUST BE NUMERIC**

Form	SES / ACI / EUSA / TRANSPORT / EVC
Region	ALL
Type Change	NEW
Field	UNI MAXIMUM SERVICE FRAME SIZE – (UNI-MSFS) AND MAXIMUM SERVICE FRAME SIZE – (MSFS)
Description	CONTENT VALIDATION FOR UNI-MSFS IF FIELD CONTAINS ALPHA, EMBEDDED BLANKS, OR SPECIAL CHARACTERS
Last Update	3/20/15

EDIT	**ICS1866E**
EDIT Message	**CEV-P VALID ENTRIES: D OR E**
Form	EVC
Region	ALL
Type Change	NEW
Field	CE-VLAN IDENTIFICATION PRESERVATION (CEV-P)
Description	CONTENT VALIDATION
Last Update	3/20/15

EDIT	**ICS0058E**
EDIT Message	**CEV-CP VALID ENTRIES: D OR E**
Form	EVC
Region	ALL
Type Change	NEW
Field	CE-VLAN CLASS OF SERVICE PRESERVATION – (CEV-CP)
Description	CONTENT VALIDATION
Last Update	3/20/15

EDIT	**ISC0756E**
EDIT Message	**BUM-FD VALID ENTRIES C, D AND U**
Form	EVC
Region	ALL
Type Change	NEW
Field	BROADCAST, UNICAST AND MULTICAST FRAME DELIVERY – (BUM-FD)
Description	CONTENT VALIDATION
Last Update	3/20/15

EDIT	**ICS1747E**
EDIT Message	**FROM: SCREEN NOT VALID FOR REQTYP** **TO: RECORD/SCREEN NOT VALID FOR REQTYPE**

Form	N/A – This is for Mech Spec Transmission of ASRs
Region	ALL
Type Change	MODIFY
Field	F44A SALI RECORD
Description	Note: This edit message modification is due to the following process change: Modify the processing of the F44A/B Mech Spec Service Address Location Information (SALI) records to accommodate ordering of Switched Ethernet Service. The following change applies to the processing of ASRs where the first position of REQTYP is "E" and the SEI field is 'Y: •Modify the inbound record processing to reject an 'F44A' record in conjunction with an 'L' record when the first position of the REQTYP on the 'S' record is 'E' and the SEI field is 'Y'. Due to this change, ICS1747E will be applicable.
Last Update	3/20/15

ASOG51 Release Error Code Section – November 19th, 2015

EDIT	**ICS1859E**
EDIT Message	**CHANGE FROM:** **UNI-MSFS FIELD MUST BE NUMERIC** **CHANGE TO:** **MSFS FIELD MUST BE NUMERIC**
Form	EVC
Region	ALL
Type Change	CHANGE
Field	MSFS
Description	CONTENT VALIDATION
Last Update	9/19/15

EDIT	**ICS1898E**
EDIT Message	**CBS-I / EBS-I FIELD MUST BE NUMERIC**
Form	EVL
Region	ALL
Type Change	NEW
Field	COMMITTED BURST SIZE (INGRESS) CBS-I
Description	CONTENT VALIDATION
Last Update	9/19/15

EDIT	ICS 1899E
EDIT Message	CMI-I FIELD VALID ENTRIES: D OR E
Form	EVL
Region	ALL
Type Change	NEW
Field	COLOR MODE IDENTIFIER (INGRESS) CMI-I
Description	CONTENT VALIDATION
Last Update	9/19/15

EDIT	ICS1897E
EDIT Message	BCF-I FIELD VALID ENTRIES: D OR E
Form	EVL
Region	ALL
Type Change	NEW
Field	BANDWIDTH COUPLING FLAG (INGRESS) BCF-I
Description	CONTENT VALIDATION
Last Update	9/19/15

ASOG52 Release Error Code Section – March 19th, 2016

EDIT	ISC1901E
EDIT Message	EDA MUST HAVE VALUE BLANK, N OR Y
Form	ASR
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	ICS1902E
EDIT Message	P-BITC-I VALID VALUES G, Y AND BLANK
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	ICS1903E
EDIT Message	P-BITC-E VALID VALUES 0 THROUGH 7, BLANK
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	ICS1904E
EDIT Message	P-BITC-E POSITIONS 1 AND 2 MUST NOT MATCH
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	ICS1905E
EDIT Message	VALID VALUES FOR CI: DEI OR PCP
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	ICS1906E
EDIT Message	VALID VALUES FOR MCLAG: D, E OR N
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	ICS1907E
EDIT Message	MCLAG ENTRY OF D IS APPLICABLE ONLY IF LAG IS D
Form	SES

Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/2016

EDIT	**ICS1908E**
EDIT Message	**MCLAG ENTRY OF E IS APPLICABLE ONLY IS ASR ACTIVITY IS C, D, OR N**
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/16

EDIT	**ICS1909E**
EDIT Message	**MCLAG ENTRY OF N IS APPLICABLE ONLY IS LAG ENTRY IS N**
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/16

EDIT	**ICS1910E**
EDIT Message	**MCLAG-P VALID ENTRIES: AA OR AS**
Form	SES
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED
Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/16

EDIT	**ICS1911E**
EDIT Message	**GETO MUST HAVE VALUE: A, E, F, M, N, O, P, R, S, T, U, V, W, Y, OR Z**
Form	ASR, TRANSPORT
Region	ALL
Type Change	NEW
Field	REQUISITION TYPE / PRODUCT BEING ORDERED

Description	CONTENT VALIDATION AT REQTYPE LEVEL
Last Update	3/19/16

ASOG53 Release Error Code Section – September 19th, 2016
No new errors

ASOG54 Release Error Code Section – March 18th, 2017
No new errors

ASOG55 Release Error Code Section – September 18th, 2017
No new errors

ASOG56 Release Error Code Section – March 17h, 2018
No new errors

ASOG57 Release Error Code Section – September 15th, 2018
No new errors

ASOG58 Release Error Code Section – March 16, 2019
No new errors

ASOG59 Release Error Code Section – September 21th, 2019

EDIT	**ICS7219E**
EDIT Message	**ATT DOES NOT SUPPORT LOSACT = "R"**
Form	EVC
Region	ALL
Type Change	NEW
Field	LOSACT
Description	Remove or update with ATT supported valid entries
Last Update	9/21/19

Updated error **ICS7112E** to add SPEC codes starting with OEM++

ASOG60 Release Error Code Section – March 21, 2020
No new errors

ASOG61 Release Error Code Section – September 19, 2020
No new errors

ASOG62 Release Error Code Section – March 20, 2021

EDIT	**ICS0220E**
EDIT Message	**VTAI valid values are A, B, C**
Form	ASR, MEC

Region	ALL
Type Change	NEW
Field	VTAI, OECVTAI
Description	Update with supported ASOG valid entries
Last Update	3/20/21

ASOG63 Release Error Code Section – September 18, 2021

No new errors